

Al igual que antes, usamos una combinación de RC y Sallen-Key

$$\Rightarrow H_1(s) = \frac{1}{s^2 + s \cdot \frac{1}{0.55} + 1} \quad \text{con } R_N = R_{2N} = 1 \quad \text{con } R_N = R_{2N} = 1$$

$$\cdot \frac{1}{0.55} = \frac{1}{C_2 \left(\frac{1}{R_1} + \frac{1}{R_2} \right)} \Rightarrow \underline{C_2N = 1.1} \quad \cdot 1 = \frac{1}{C_1 R_1 R_2} \Rightarrow \underline{C_1N = 0.909}$$

$$\Rightarrow H_2(s) = \frac{1}{s^2 + s \cdot \frac{1}{0.8} + 1} \quad \text{con } R_{3N} = R_{4N} = 1$$

$$\cdot \frac{1}{0.8} = \frac{1}{C_4 \left(\frac{1}{R_3} + \frac{1}{R_4} \right)} \Rightarrow \underline{C_4N = 1.6} \quad \cdot 1 = \frac{1}{C_3 R_3 R_4} \Rightarrow \underline{0.625 = C_3N}$$

$$\Rightarrow H_3(s) = \frac{1}{s^2 + s \cdot \frac{1}{2.25} + 1} \quad \text{con } R_{5N} = R_{6N} = 1$$

$$\cdot \frac{1}{2.25} = \frac{1}{C_6 \left(\frac{1}{R_5} + \frac{1}{R_6} \right)} \Rightarrow \underline{C_6N = 4.5} \quad \cdot 1 = \frac{1}{C_5 C_6 R_5 R_6} = \underline{0.22N = C_5N}$$

$$\Rightarrow H_4(s) = \frac{1}{s^2 + \frac{1}{RC} s + 1} \quad \text{con } R_{7N} = 1 \wedge C_{7N} = 1$$

→ Ahora desnormalizamos con $Z_N = 1K$ y $S_N = \omega_N = 2\pi \cdot 57$

$$\cdot R_1 = R_2 = R_3 = R_4 = R_5 = R_6 = R_7 = \underline{1K\Omega}$$

$$\cdot C_1 = \frac{C_1N}{Z_N S_N} = \underline{38.26nF} \quad \cdot C_2 = \underline{46.3nF} \quad \cdot C_3 = \underline{26.31nF} \quad \cdot C_4 = \underline{67.35nF}$$

$$\cdot C_5 = \underline{90.26nF} \quad \cdot C_6 = \underline{189.4nF} \quad \cdot C_7 = \underline{42.1nF}$$