

PCB Ordering instructions:

Go to <u>JLCPCB instant quote</u> and add Gerber file (Figure 1a). Select default settings and preferred PCB color (Figure 1b). Under PCB settings select SMT assembly and indicate quantity (2 or 5) (Figure 1c).

a



b



C




Figure 1

Click next and add the BOM and PnP files (Figure 2a-b).


Click next and review if any parts are unavailable. If yes, order from a different supplier (e.g. Mouser, Farnell, Digikey ...). (Figure 2c).

Click next to see the position of each part on the PCB; save to cart and complete payment (Figure 3).





b



C

Uploaded BOM Data			Review Matched Parts						
Designator	Name	Footprint	Matched Part Detail		Qty	Source	Lib Type	Total Cost	Select @
C6	470 n F	C0805	CL21B474KBFNNNE C13967 50V 470nF X7R ±10% 0805 Multilayer	Q	20	JLCPCB	Basic	£ 0.2213 @	V
sw2	TS-1187A-B-A-B	SW-SMD_4P-L5.1	TS-1187A-B-A-B C318884 No NO 50mA 5.1mm 100mΩ 100000 160gf	Q	5	JLCPCB	Basic	€ 0.0622 ◎	~
R9	22K	R0805	0805W8F2202T5E C17560 ±1% 125mW Thick Film Resistors 150V	Q	20	JLCPCB	Basic	£ 0.0415 @	~
C7,C4	10nF	C0805	CL21B103KBANNNC C1710 50V 10nF X7R ±10% 0805 Multilayer C	Q	20	JLCPCB	Basic	£ 0.0938 ◎	~
U1	L9958XP	POWERSSO- 24_L10	L9958XP C443848 PowerSSO-24 Motor Driver ICs ROHS	Q	2	JLCPCB	Extended	€ 10.7481 🕜	Inventory short
C10,C11,C1	1uF	C0805	CL21B105KBFNNNE C28323 50V 1uF X7R ±10% 0805 Multilayer Ce	Q	20	JLCPCB	Basic	£ 0.1429 @	~
R17,R19,R2	1.8K	R0805	0805W8F1801T5E C17398 ±1% 125mW Thick Film Resistors 150V	Q	20	JLCPCB	Basic	£ 0.0354 @	~
U4,U9	MAX31855KASA+T	SO-8_L4.9-W3.9	MAX31855KASA+T C52028 SO-8 ADC/DAC - Specialized ROHS	Q	4	JLCPCB	Extended	£ 16.5553 @	✓

Figure 2




Figure 3