

LAB 4 ROUTER CONFIGURATIONS

GURUCHANDHRAN M

TASK 1: INTERFACE IP CONFIGURATION

ROUTER IP: 50.0.0.1

The screenshot displays a network simulation environment. On the left, a network diagram shows a router labeled 'ROUTER' with IP address '50.0.0.1' connected to a PC labeled 'Win' with IP address '50.0.0.10'. The connection is labeled 'SSH - TELNET'. The router is also labeled 'SUN SUREN NETWORK'. On the right, a terminal window titled 'ROUTER' shows the following commands and output:

```
ROUTER#conf t
Enter configuration commands, one per line. End with CNTL/Z.
ROUTER(config)#int ethernet 0/0
ROUTER(config-if)#ip address 50.0.0.1 255.0.0.0
ROUTER(config-if)#no shutdown
ROUTER(config-if)#exit
ROUTER(config)#exit
ROUTER#
*Jul 11 06:33:22.185: %SYS-5-CONFIG_I: Configured from console by console
ROUTER#write memory
Building configuration...
[OK]
ROUTER#show ip int brief
Interface IP-Address OK? Method Status Prot
0c01
Ethernet0/0 50.0.0.1 YES manual up up
Ethernet0/1 unassigned YES TFTP down down
Ethernet0/2 unassigned YES TFTP down down
Ethernet0/3 unassigned YES TFTP down down
```

The status bar at the bottom indicates 'Router Configuration' and 'Physical'.

TASK 2: CREATING CONSOLE PASSWORD

The screenshot displays a network simulation environment. On the left, a network diagram shows a router labeled 'ROUTER' with IP address '50.0.0.1' connected to a PC labeled 'Win' with IP address '50.0.0.10'. The connection is labeled 'SSH - TELNET'. The router is also labeled 'SUN SUREN NETWORK'. On the right, a terminal window titled 'ROUTER' shows the following commands and output:

```
ROUTER#conf t
Enter configuration commands, one per line. End with CNTL/Z.
ROUTER(config)#username guru password madam
ROUTER(config)#line console 0
ROUTER(config-line)#password techy
^
Invalid input detected at '^' marker.
ROUTER(config-line)#password techy
ROUTER(config-line)#login local
ROUTER(config-line)#exit
ROUTER(config)#exit
ROUTER#
*Jul 11 06:40:51.465: %SYS-5-CONFIG_I: Configured from console by guru on console
ROUTER#write memory
Building configuration...
[OK]
ROUTER#exit
```

The status bar at the bottom indicates 'Router Configuration' and 'Physical'.

TASK 3: ENABLING SECRET PASSWORD

The screenshot displays a network simulation environment. At the top, a network diagram shows a router connected to a PC via a serial link labeled "SSH - TELNET". The router's IP is 60.0.0.1 and the PC's IP is 60.0.0.10. Below the diagram, a terminal window titled "ROUTER" shows the configuration process:

```
User Access Verification
Username: guru
Password:
ROUTER>en
ROUTER#conf t
Enter configuration commands, one per line. End with CNTL/Z.
ROUTER(config)#enable secret techy
ROUTER(config)#exit
ROUTER#write
*Jul 11 06:42:08.765: %SYS-5-CONFIG_I: Configured from console by guru on console
ROUTER#write memory
Building configuration...
[OK]
ROUTER#exit
```

At the bottom, a larger terminal window titled "ROUTER" shows the user access verification process:

```
ROUTER con0 is now available

Press RETURN to get started.

User Access Verification

Username: guru
Password:
ROUTER>en
Password:
ROUTER#
```

TASK 4: ENABLING TELNET

The screenshot displays a network simulation interface. On the left, a network diagram shows two routers connected by a link. The left router is labeled 'ROUTER' with IP '50.0.0.1' and the right router is labeled 'Win' with IP '50.0.0.10'. Above the link, the text 'SSH - TELNET' is displayed. On the right, a terminal window titled 'ROUTER' shows the following commands and output:

```
Press RETURN to get started.  
User Access Verification  
Username: guru  
Password:  
Password:  
ROUTER#conf t  
Enter configuration commands, one per line. End with CNTL/Z.  
ROUTER(config)#line vty 0 4  
ROUTER(config-line)#transport input telnet  
ROUTER(config-line)#password telnet  
ROUTER(config-line)#login  
ROUTER(config-line)#exit  
ROUTER(config)#exit  
ROUTER#  
*Jul 11 06:46:04.084: %SYS-5-CONFIG_I: Configured from console by guru on console  
ROUTER#write memory  
Building configuration...  
(OK)  
ROUTER#
```

At the bottom of the interface, there is a 'Router Configuration' button and a 'Physical' tab with a slider and a 'START' button.

TELNET VERIFICATION

The screenshot displays a network simulation interface. On the left, a network diagram shows two routers connected by a link. The left router is labeled 'ROUTER' with IP '50.0.0.1' and the right router is labeled 'Win' with IP '50.0.0.10'. Above the link, the text 'SSH - TELNET' is displayed. On the right, a terminal window titled 'ROUTER' shows the following commands and output:

```
Press RETURN to get started.  
User Access Verification  
Username: guru  
Password:  
Password:  
ROUTER#conf t  
Enter configuration commands, one per line. End with CNTL/Z.  
ROUTER(config)#line vty 0 4  
ROUTER(config-line)#transport input telnet  
ROUTER(config-line)#password telnet  
ROUTER(config-line)#login  
ROUTER(config-line)#exit  
ROUTER(config)#exit  
ROUTER#  
*Jul 11 06:46:04.084: %SYS-5-CONFIG_I: Configured from console by guru on console  
ROUTER#write memory  
Building configuration...  
(OK)  
ROUTER#
```

On the right, a QEMU (Win) window shows a Windows desktop environment. A terminal window titled 'Win' is open, displaying the following commands and output:

```
User Access Verification  
Username: guru  
Password:  
Password:  
ROUTER#conf t  
Enter configuration commands, one per line. End with CNTL/Z.  
ROUTER(config)#show ip int brief  
ROUTER#  
Invalid input detected at '' marker.  
ROUTER(config)#exit  
ROUTER#show ip int brief
```

Interface	IP-Address	OK?	Method	Status	Port
Ethernet0/0	50.0.0.1	YES	manual	up	up
Ethernet0/1	unassigned	YES	TFTP	down	down
Ethernet0/2	unassigned	YES	TFTP	down	down
Ethernet0/3	unassigned	YES	TFTP	down	down

At the bottom of the interface, there is a 'Router Configuration' button and a 'Physical' tab with a slider and a 'START' button.