
24. Finite State Machines

Reading FSM Diagrams

You can get a feel for how FSM diagrams work by studying the following simple example:



This diagram represents the following rule:

In state S_0,
if input = 1, then output = 1, and return to S_0;
if input = 0, then output = 1, and move to S_1.

In state S1, halt on any input.

Constructing FSM Diagrams

FSM diagrams can be constructed from the following elements.


Nodes: circles associated with names.

- Each node represents a state.
- The initial state is always named "S_0".



Links: one-directional arrows connecting circles to circles.


- There are at most two lines leaving each circle.*
- There may be zero lines leaving a circle.
- Circles can be connected to themselves.
- The lines can cross.



*More precisely, there are as many lines leaving each circle as possible inputs. If the machine can read *n* symbols, there will be up to *n* links for each node.


Labels: each line is labeled with with an expression of the form "*input* : *output*".

- Possible inputs: 1, 0
- Possible outputs: 1, 0.
- **Note!** For each circle, there can be at most one arrows labeled with input 1, and one arrows labeled with input 0.
- A common variation writes the output where we've put the state name, and labels the line only with the input.




Loops: any kind of loop is acceptable:

- Loops from a state to itself.
- Loops among a groups of states.



Halting:

- A machine halts in a given state, given an input, if there are no arrows leaving that state for that input.
- If there are *no* lines leaving a state, the machine will halt in that state no matter what.




Computing with Finite State Machines

Computation for FSMs is defined in the same way as it is for SCs. Local inputs and outputs are processed one bit at a time, and the global input and output corresponds to the sequences of inputs and outputs which is reached when all further input and output bits will be 0s.


Note on halting:

- A machine **halts** in a given state, given an input, if there are no arrows leaving that state for that input.
- When computing a function, an FSM should never halt. Instead, it should end computation by outputting 0's indefinitely.


So **don't** design your FSM this way.



Do ensure that the final state produces a continuous output of 0's:



To compute tally successor…





+1 T

Example: +1 T

This FSM at right computes successor in tally.

The timeline below shows the step-by-step progression of the machine for a sample input.






IN

0 0 0 1 1

OUT

1 1




IN

0 0 0 1 1

OUT

1 1 1




IN

0 0 0 1 1

OUT

0 1 1 1




IN

0 0 0 1 1

OUT


0 0 1 1 1



Example: +1 B

This FSM at right computes successor in binary.

The timeline below shows the step-by-step progression of the machine for a sample input.




+1 B

IN

0 0 1 1

OUT

0




IN

0 0 1 1

OUT

0 0




IN

0 0 1 1

OUT

1 0 0



IN

0 0 1 1

OUT

0 1 0 0

