

ECE 341
Homework 4

The problem numbers listed below are from the Lathi textbook, 3rd edition.

Prob. Number	Course Outcome	Grade
4.1-1 (a) (d)	1-c, 7-c	/ 20
4.1-4 (a)	1-c, 7-c	/ 10
4.2-2 (a) (b)	1-c, 7-c	/ 20
4.3-1 (b)	1-c, 7-c	/ 15
4.4-7	1-c, 7-c	/ 20
4.8-2	1-c, 7-c	/ 15
TOTAL:		/ 100

1-c. Use Laplace, Z, and Fourier transforms to obtain the frequency domain models to represent signals and systems.

7-c. Apply new knowledge to understand continuous and discrete systems.

- 4.1.1 a) First, we may split the given function into two integrals, on the interval where the given unit functions resolve to non-zero values, as

$$\int_0^{\infty} u(t)e^{-st} dt - \int_1^{\infty} u(t-1)e^{-st} dt = \int_0^{\infty} e^{-st} dt - \int_1^{\infty} e^{-st} dt.$$

Then, evaluating the integrals,

$$\begin{aligned} &= \left. \frac{-e^{-st}}{s} \right|_0^{\infty} + \left. \frac{e^{-st}}{s} \right|_1^{\infty} \\ &= \left[\frac{-e^{-s\infty}}{s} + \frac{1}{s} \right] + \left[\frac{e^{-s\infty}}{s} - \frac{e^{-s}}{s} \right] \\ &= \frac{1 - e^{-s}}{s}. \end{aligned}$$

- d) Again, splitting the given function into two integrals,

$$\int_0^{\infty} e^{-2t}e^{-st}u(t) dt - 2 \int_0^{\infty} e^{-t}e^{-st}u(t) dt = \int_0^{\infty} -e^{-t(s+2)} dt + 2 \int_0^{\infty} e^{-t(s+1)} dt.$$

Then, evaluating the integrals,

$$\begin{aligned} &= -\left. \frac{e^{-2t}e^{-st}}{s+2} \right|_0^{\infty} + \left. \frac{2e^{-t}e^{-st}}{s+1} \right|_0^{\infty} \\ &= \frac{1}{s+2} + \frac{2}{s+1}. \end{aligned}$$

- 4.1.4 a) Using partial fraction decomposition,

$$\frac{2s+5}{s^2+5s+6} = \frac{2s+5}{(s+2)(s+3)} = \frac{A}{(s+2)} + \frac{B}{(s+3)}$$

$$2s+5 = A(s+3) + B(s+2) = sA + 3A + sB + 2B$$

$$2s+5 = s(A+B) + 3A+2B.$$

Solving for A and B , $A+B=2$ and $3A+2B=5$, so

$$\begin{bmatrix} 1 & 1 & 2 \\ 3 & 2 & 5 \end{bmatrix} \rightarrow \begin{bmatrix} 1 & 0 & 1 \\ 0 & 1 & 1 \end{bmatrix},$$

and so $A=1$ and $B=1$.

Therefore,

$$\frac{2s+5}{s^2+5s+6} = \frac{1}{(s+2)} + \frac{1}{(s+3)},$$

and the inverse Laplace transform of the function may be found using Table 4.1, specifically the unilateral transform pair $1/(s-\lambda) \Leftrightarrow e^{\lambda t}u(t)$,

$$\begin{aligned} \mathcal{L}^{-1} \left\{ \frac{1}{s+2} + \frac{2}{s+1} \right\} &= \mathcal{L}^{-1} \left\{ \frac{1}{s+2} \right\} + \mathcal{L}^{-1} \left\{ \frac{1}{s+3} \right\} \\ &= e^{-2t} + e^{-3t}. \end{aligned}$$

- 4.2.2 a) Using the Laplace transform pair $u(t) \Leftrightarrow 1/s$ and the time-shifting property of the Laplace transform, $x(t - t_0) \Leftrightarrow X(s)e^{-st_0}$,

$$\begin{aligned}\mathcal{L}\{u(t) - u(t - 1)\} &= \mathcal{L}\{u(t)\} - \mathcal{L}\{u(t - 1)\} \\ &= \frac{1}{s} - \frac{e^{-s}}{s} = \frac{1 - e^{-s}}{s}.\end{aligned}$$

- b) Likewise, using the time-shifting property of the Laplace transform along with the Laplace transform pair $e^{\lambda t}u(t) \Leftrightarrow 1/(s - \lambda)$,

$$\mathcal{L}\left\{e^{-(t-\tau)}u(t - \tau)\right\} = \frac{e^{-s\tau}}{s - t}.$$

- 4.3.1 b) Converting to differential form,

$$\ddot{y}(t) + 4\dot{y}(t) + 4y(t) = \frac{d}{dt}e^{-t}u(t) + e^{-t}u(t)$$

with initial conditions

$$y(0^-) = \dot{y}(0^-) = 0,$$

the time differentiation property of the Laplace transform may be used along with the transform pair $e^{\lambda t}u(t) \Leftrightarrow 1/(s - \lambda)$ to find

$$\begin{aligned}\mathcal{L}\{\ddot{y}(t) + 4\dot{y}(t) + 4y(t)\} &= \mathcal{L}\left\{\frac{d}{dt}e^{-t}u(t) + e^{-t}u(t)\right\} \\ &= [s^2Y(s) - sy(0^-) - \dot{y}(0^-)] + 4[sY(s) - y(0^-)] + 4Y(s) = sX(s) - x(0^-) + \frac{1}{s+1} \\ &= s^2Y(s) + 4sY(s) + 4Y(s) = \frac{s+1}{s+1} = 1 \\ &= Y(s)[s^2 + 4s + 4] = 1.\end{aligned}$$

Solving algebraically for $Y(s)$,

$$Y(s) = \frac{1}{s^2 + 4s + 4} = \frac{1}{(s+2)^2},$$

which may be solved directly using the Laplace transform pair $te^{\lambda t}u(t) \Leftrightarrow 1/(s - \lambda)^2$, as

$$\mathcal{L}^{-1}\left\{\frac{1}{(s+2)^2}\right\} = te^{-2t}u(t).$$

- 4.4.7 At $t < 0$, before the switch has opened, we may derive the initial conditions of the circuit as

$$\begin{aligned}v_s(0^-) &= 0^V \\ y(0^-) &= 10^A \\ y_2(0^-) &= 0^A.\end{aligned}$$

After the switch opens, at $t > 0$, we may derive the voltage across each component using the voltage equations for inductors, resistors, and capacitors,

$$\begin{aligned}v_R(t) &= Ri(t) \\ v_L(t) &= L\frac{di_L(t)}{dt} \\ v_C(t) &= \frac{1}{C}\int i(t) + v_0,\end{aligned}$$

along with the unilateral Laplace transform pairs

$$\begin{aligned} a &\Leftrightarrow \frac{a}{s} \\ x(t) &= X(s) \\ \frac{dx(t)}{dt} &\Leftrightarrow sX(s) + x(0^-) \\ \int_{0^-}^t x(\tau)d\tau &\Leftrightarrow \frac{1}{s}X(s) \end{aligned}$$

to derive the loop equation for the circuit at $t > 0$,

$$\begin{aligned} \frac{10}{s} &= [2sY(s) - 10] + sY(s) + \frac{1}{s}Y(s) + Y(s) \\ &= Y(s) \left[3s + \frac{1}{s} + 1 \right] - 10, \end{aligned}$$

so that

$$\begin{aligned} Y(s) &= \frac{10}{s} \left[\frac{1}{3s + \frac{1}{s} + 1} \right] + 10 \\ &= \frac{10}{3s^2 + s + 1} + 10. \end{aligned}$$

Before converting back to the time domain, we may solve for $V_s(s)$ using Ohm's Law, as

$$V_s(t) = Y(s) \left[s + \frac{1}{s} \right] = Y(s)s + \frac{Y(s)}{s}.$$

Transforming $Y(s)$ back to the time domain by factoring and using partial fraction decomposition,

$$\begin{aligned} Y(s) &= \frac{10}{3s^2 + s + 1} + 10 \\ &= \frac{10}{(s+1)(s^2+1)} \\ &= \frac{As+B}{(s+1)(s^2+1)} \end{aligned}$$