

Single-Line Diagram — Meadowbank Solar + Storage

15 MW PV + 10 MW BESS shared 33 kV connection

Connection point	Shared 33 kV metered busbar
PV array	15 MW
BESS	10 MW / 20 MWh
Coupling	AC-coupled on shared bus
Drawing ref	MB-SLD-06, Rev B

1. Shared connection

The PV array (15 MW) and BESS (10 MW / 20 MWh) are combined onto a common 33 kV switchboard sharing a single metered point of connection. A site controller enforces the combined 15 MW export limit.

2. BESS coupling and charge path

2.1 The BESS inverters are connected to the shared 33 kV AC bus through a bidirectional breaker. With the PV array offline, the BESS can charge from the grid through this path; there is no DC-coupling that would physically restrict charging to PV only.

2.2 No interlock is shown that would prevent grid import to the BESS when PV generation is zero.

Connection schedule

Asset	Rating	Coupling	Charge source
PV array	15 MW	AC, shared bus	—
BESS	10 MW / 20 MWh	AC, shared bus	PV or grid (no interlock)
Export limit (controller)	15 MW firm	metered POC	—