

Interface Protection Settings — Riverside BESS

11 kV point of connection

Point of connection	11 kV ring main unit
Standard	ENA G99 Issue 2
Loss of mains	RoCoF 1.0 Hz/s, 0.5 s

1. Anti-islanding

Loss-of-mains protection is provided by a RoCoF element set at 1.0 Hz/s with a 0.5 s confirmation time, co-ordinated with the DNO 11 kV scheme.

Settings table

Function	Setting	Time delay
Loss of mains (RoCoF)	1.0 Hz/s	0.5 s
Undervoltage U<	-13%	2.5 s
Undervoltage U<	-20%	0.5 s
Overvoltage U>	+10%	1.0 s
Overvoltage U>	+13%	0.5 s
Underfrequency f<	47.5 Hz	20 s
Underfrequency f<	47.0 Hz	0.5 s
Overfrequency f>	51.5 Hz	90 s