

# Interface Protection Settings — Riverside BESS

11 kV point of connection

---

Loss of mains: RoCoF 1.0 Hz/s, 0.5 s confirmation time.

Voltage:  $U < -13\%$  2.5 s,  $U < -20\%$  0.5 s,  $U > +10\%$  1.0 s,  $U > +13\%$  0.5 s.

Frequency:  $f < 47.5$  Hz 20 s,  $f < 47.0$  Hz 0.5 s,  $f > 51.5$  Hz 90 s.