

CompTIA A+ Core 1 Playbook

IT Labs

Prepared by Garrick White

4.3.9 Troubleshoot GPU

You work at a computer repair store. A customer has brought in their PC. They say the computer turns on but they can't get it to display on the monitor.

In this lab, your task is to diagnose the problem and implement a fix so the computer displays properly.

Complete this lab as follows:

1. Test the computer.
 1. Press the power button on the computer. The computer turns on, but the monitor doesn't get a signal.
 2. Press the power button again to turn the computer off.
2. Check the connection to the monitor.
 1. Switch to the **Back** views of the computer and monitor. Verify that they are connected to each other.
 2. They are connected, so this is not the problem. Switch back to the **Front** view of the computer.
3. Check the GPU.
 1. Switch to the **Motherboard** view of the computer.
 2. Locate the GPU. Notice that its power port is not connected to the power supply.
 3. Select the **Power Supply**.
 4. In the Selected Item pane, scroll down to find a **6-pin PCIe** connector. Drag the connector to the port on the GPU.
4. Turn on the computer.
 1. Switch to the **Front** view of the computer.
 2. Press the **power** button and wait for the OS to load. The displays correctly.