

LET Sample Examination "No. 2024 – I've had enough" 2026



1. Any two from **2.10.2.5 (c) (i) (ii) (iii) (iv)**
2. Not more than three (3) **2.6.2.4 (b) (i)**
3. 2.5mm^2 **3.5.1 Table 3.3**
4. A mains-operated fence controller complying with AS/NZS60335.2.76 **7.8.3.2**
5. 500mm **5.3.6.4 (b) Table 3.7**
6. Withdrawn from service immediately, have an out-of-service tag attached.....
Sent for repair, disposal or destruction by authorized repair agent or service personnel.
3.7.2 (a) (b)
7. (i) Precast concrete slabs having a thickness of not less than 40mm and classification of not less than grade 20 in accordance with AS 3600
(ii) Polymetric cable cover strip complying with AS 4702
225 (f) (i) (ii)
8. (i) Help should be sought by dialling 000 for an ambulance
(ii) or by asking a bystander to make the call
9. - Main Neutral not indicated on neutral bar **2.10.5.4**
- Hot water Service switch not marked as "Main Switch" **2.3.3.5 (a)**
- DB2 Isolator not rated for circuit voltage – 400V **2.2.4.2**
- DB2 Fuses are undersized for MD load ($I_b > I_n > I_z$) **2.5.3.1**
- Fuse not permitted to be installed in the neutral conductor - Hot Water Service **2.5.1.1**
- Hot Water Service conductors undersize (T10, Col2 $2.5\text{mm}^2 = 27\text{A}$) Min. size after 0.9 HRC derating = 27.78A **3.4.1**
- Main Earthing Conductor undersized for Mains actives (should be 25mm^2) **5.3.3.2 Table 5.1**
- Main Earth Electrode not suitable size **5.3.6.2 Table 5.2**
- Final subcircuit neutrals do not correspond with final subcircuit actives (neutral sequencing) **2.10.5.4**
- MAIN Switch (3 phase) not marked "ON / OFF" **2.3.2.2.1 (c)**
- MAIN Switch (3 phase) does not indicate the portion of the installation it controls **2.3.3.5 (b)**
10. Table 3 (4)
T 14 Col. 25 $50\text{mm}^2 @ 155\text{A} \times 3 = 465\text{A}$
Soil Resistivity T 29 Col. 4 = 0.95
Touching T26 (2) Col. 2 = 0.83
Spaced T26 (2) Col. 4 = 0.91
(i) 366.65A
(ii) 401.99A
11. Meter Z – 8A
Meter Y – 640W

Meter X – 40Ω

12. Table C2 Col. 2

(b) (i) (32) 10A socket outlets $1000 + (31 \times 400) = 13400/230 = 58.26A$

(b) (iii) (3) 15A socket outlets $15 + (2 \times 50\%) = 30A$

(a) (38) 15W LED downlights $38 \times 15 \times 75\% = 427.5/230 = 1.86A$

(c) (i) 3kW Instantaneous water heater FLC – $3000/230 = 13.04A$

(g) 4.5kW Spa pump heater FLC – $4500/230 = 19.56A$

Total MD = 122.72A

13. CM

Table 41 Column 10

Vc – 1.25

$11 \times 130 \times 1.25/1000$

Vd = 1.79V

SM

Table 45 Column 6

Vc – 2.54

$55 \times 50 \times 2.54/1000$

Vd = 6.99V

FSC

Table 42 Column 6

Vc – 15.6

$35 \times 28 \times 15.6/1000$

Vd – 15.29V

Total Vd = $1.79 + 6.99 + 10.37 = 24.07V$

14. Rating – $175/25 = 7$

Min. time – 0.01sec.

Max. time – 2sec.

15. Tx impedance – 0.01375Ω

MSB – $230 / (0.01375 + 0.0031) = 13649.85A$

DB – $230 / (0.01375 + 0.0031 + 0.02314) = 5751.43A$

16. No 2.6.2.1

17. B

18. Persons name, company and contact details 3.1.4.2