

LOIVA

ST-21





Button Wrapping & Knotting Machine

Introduction

1. SELF DIAGNOSES FUNCTION :- AS SOON SWITCH ON THE MACHINE THE MACHINE WILL GET SELF DIAGNOSED
2. THREE LEVEL SETTING MODE
 - 1) OPERATOR WITHOUT PASSWORD
 - !!) SUPERVISOR WITH PASSWORD
 - !!!) MASTER WITH PASSWORD
3. MACHINE SELF TESTING MODE (MASTER)
 - a) IN PUT TEST OF SENSOR
 - b) OUT PUT TEST OF SOLENOID
 - c) MOTOR RUNNING TEST
4. CYCLE TIME INDICATOR DISPLAY WILL SHOW THE CYCLE TIME OF EACH OPERATION
5. CYCLE TIME PER BUTTON THE CYCLE TIME PER BUTTON WILL BE 3.8 SECOND WITH 15WRAPS AND 4 KNOTS
6. TRIMMING MECHANISM SCISSOR TYPE TRIMMING MACHINIST WHICH ENSURES SHORT TRIMMING WITHOUT HITTING THE BUTTON AND ONLY ONE THREAD VISIBLE
7. ANTI LOOSE KNOT HIGH TORQUE MOTOR ENSURES PERFECT KNOTS
8. HEAVY DUTY SMPS WITH LINEAR POWER SUPPLY THE REGID POWER SUPPLY WHICH CAN WITH STAND VOLTAGE FLUCTUATIONS AND TEMPERATURE CONDITIONS
9. WORKING LIGHT THE MACHINE IS HAVING BUILT IN WORKING LIGHT TO EASE THE THREADING OPERATION
10. PRODUCTION COUNTER
 - a) DAILY PRODUCTION COUNTER THIS CAN BE RESET BY USER
 - b) MASTER PRODUCTION COUNTER THIS CANNOT BE RESET BY USER
11. THE STEPPING MOTOR AND DRIVES STANDARD STEPPING MOTORS AND DRIVES ARE USED AND THESE DRIVES AND MOTORS ARE COMPATIBLE WITH EASILY AVAILABLE DRIVES IN THE MARKET.
12. INCLINED DISPLAY THE DISPLAY IS INCLINED TO AVOIDED DIRECT CONTACT WITH OPERATOR
13. PNEUMATICS ALL THE PNEUMATIC PARTS ARE MANUFACTURED BY SMC WHICH ENSURES QUALITY AND EASY AVAILABILITY IN FUTURE.

Display Type : Colour Tft Touch Screen Hmi
Wrapping Mechanism: Stepping Motor Driven
Knotting Mechanism: Stepping Motor Driven
Oscillation Mechanism: Stepping Motor Driven
Power Supply: Smps With Linear Power Supply
Wrapping Speed: 10-3000 Rpm
Knotting Speed: 100-1400 Rpm
Input Voltage: 230 Vac
Current: 1amp
Frequency: 50hz
Air Pressure: 5bars
Button Type: Flat Or Shank
Wrapping Frequency: 1-200 Turns
Knotting Frequency: 1-30 Turns
Initial Knotting: 1 Or 2 Selectable
Trimmer: Scissor Type
Stepping Motor Drive: Pic And Mosfet Based
Power Supply: Smps Controlled With Micro Controller



Button Wrapping & Knotting