6. We should not measure voltage or current in ohm's range. Otherwise, the meter will become faulty.
7. While measuring, the angle of vision towards the meter should be straight. Otherwise, parallax error will result in the measuring quantities.

DO YOU KNOW?

While taking measurements in a scale, the angle of vision towards the scale should also be straight. If we see the scale from sidewards, measurements will be wrong.

Like this, in an analog multimeter, if the angle of vision towards the meter be straight, the measurement will be accurate.

8. We should not measure high voltage or current by keeping one probe at the supply and the other probe's metal point in contact with our hand, which will result in fatal electric shock.
9. We should presume the voltage and current to be measured at a point of circuit. If any doubt arises, we should first select high range and then measure it. If it is a low voltage, then we select the lower ranges for measuring.

DO YOU KNOW?

We can also measure Extra High tension voltage up to 30 kilo Volts using ordinary multimeter. How? Using EHT probes, we can measure the above said range. EHT probes have a multiplier resistance value above 100 MΩ. The multiplier reduces the EHT voltage and the reduced voltage is applied to the meter. Now, we can measure the voltage reading.

Warning !

Don't try to measure EHT voltage using ordinary probes. It is shock *hazardous*.

10. High voltage must not be measured using low voltage range. Otherwise the meter will become faulty.

DO YOU KNOW?

Selecting the Colour of the Probe

While using multimeters, we frequently ask a question within our mind. What happens if we connect **black probe** to **positive socket** of the meter and **red probe** to **negative socket** during measurement?

Nothing will happen

Apart from the colours, they are just wires. But, meter should be connected in correct polarities with the circuit. The concept **Black probe** should be connected with **negative socket** and **red probe** to **positive socket** of the meter is accepted all over the world. So, we use this concept.

Uses of Analog Multimeter

1. It is used in trouble shooting Radio, TV and all other electronics equipment.
2. It is also used to check electrical appliances.
3. It is used in assembling of electronics equipment.
4. It is used in installation of electronics equipment.
5. It is used to measure A.C and DC voltages and currents and resistance.

Calibration

Calibration is a process of correcting a faulty meter using a properly functioning multimeter. In this process, burnt resistors and defective components are replaced and the movement of the coil is also smoothened. In companies, this process is often done to maintain accuracy and quality of their products.

ELEC_EQUIP_Chapter10.indd 209 11/10/2020 11:55:37 AM