Model Tabular column for an NPN Transistor using Analog Multimeter

S.No.	Selector switch position	Emitter	Base	Collector	Meter Reading	Result
1	X 1	+ve probe	-ve Probe	----	7 Ω	Good
2	X 1	----	-ve Probe	+ve probe	7 Ω	Good
3	X 1 K	-ve Probe	+ve probe	----	∞ Ω	Good
4	X 1 K	----	+ve probe	-ve Probe	∞ Ω	Good
5	X 1 K	-ve Probe	----	+ve probe	∞ Ω	Good
6	X 1 K	+ve probe	----	-ve Probe	∞ Ω	Good
Final Result: Good condition. This transistor can be used in circuits.						

Tabular column for transistor testing (NPN – BC 548)

S.No.	Selector switch position	Emitter	Base	Collector	Meter Reading	Result
1	X 1	+ve probe	-ve Probe	----		
2	X 1	----	-ve Probe	+ve probe		
3	X 1 K	-ve Probe	+ve probe	----		
4	X 1 K	----	+ve probe	-ve Probe		
5	X 1 K	-ve Probe	----	+ve probe		
6	X 1 K	+ve probe	----	-ve Probe		
Final Result:						

Tabular column for transistor testing (PNP – BC 558)

S.No.	Selector switch position	Emitter	Base	Collector	Meter Reading	Result
1	X 1	-ve Probe	+ve probe	----		
2	X 1	----	+ve probe	-ve Probe		
3	X 1 K	+ve probe	-ve Probe	----		
4	X 1 K	----	-ve Probe	+ve probe		
5	X 1 K	-ve Probe	----	+ve probe		
6	X 1 K	+ve probe	----	-ve Probe		
Final Result:						

Result:

The testing of semiconductor diode, zener diode, NPN and PNP transistors are studied.

EE_Practicals_English Version.indd 255 11/10/2020 12:17:47 PM