Example Add: $1011_2 + 1001_2$

(Carry Bit)→ 1 1

	1	0	1	1	} 1 0
+	1	0	0	1	
1	0	1	0	0	

$1011_2 + 1001_2 = 10100_2$

Example Perform Binary addition for the following: $23_{10} + 12_{10}$

Step 1: Convert 23 and 12 into binary form

23_{10}

2's power	16	8	4	2	1
Binary Number	1	0	1	1	1

$23_{10} = 00010111_2$

12_{10}

2's power	8	4	2	1
Binary Number	1	1	0	0

$12_{10} = 00001100_2$

Step 2: Binary addition of 23 and 12:

Carry Bit →			1	1	1		
$23_{10} = 0$	0	0	1	0	1	1	1
$12_{10} = 0$	0	0	0	1	1	0	0
$35_{10} = 0$	**0**	**1**	**0**	**0**	**0**	**1**	**1**

2.6.2 Binary Substraction

The table for Binary Substraction is as follows:

A	B	Difference (A-B)	Borrow
0	0	0	0
1	0	1	0
1	1	0	0
0	1	1	1

When substracting 1 from 0, borrow 1 from the next Most Significant Bit, when borrowing from the next Most Significant Bit, if it is 1, replace it with 0. If the next Most Significant Bit is 0, you must borrow from a more significant bit that contains 1 and replace it with 0 and 0s upto that point become 1s.

Example Substract $1001010_2 - 10100_2$

	0	1	10	0	10		
	~~1~~	~~0~~	0	~~1~~	0	1	0
(-)			1	0	1	0	0
		1	1	0	1	1	0

Example Perform binary addition for the following: $(-21)_{10} + (5)_{10}$

Step 1: Change -21 and 5 into binary form

21_{10}

2's power	16	8	4	2	1
Binary Number	1	0	1	0	1

$21_{10} = 00010101_2$

5_{10}

2's power	4	2	1
Binary Number	1	0	1

$5_{10} = 00000101_2$

Step 2:

21_{10}	0	0	0	1	0	1	0	1
1's Compliment	1	1	1	0	1	0	1	0
2's Compliment	1	1	1	0	1	0	1	1

Step 3:

Binary Addition of –21 and 5 :

Carry bit				1	1	1	1	
-21_{10}	1	1	1	0	1	0	1	1
5_{10}	0	0	0	0	0	1	0	1
-16_{10} (Result)	1	1	1	1	0	0	0	0

Workshop

8. Perform the following binary computations:

(A) $10_{10} + 15_{10}$ (B) $-12_{10} + 5_{10}$

(C) $14_{10} - 12_{10}$ (D) $(-2_{10}) - (-6_{10})$

Chapter 2 Page 018-050.indd 24 3/20/2020 10:42:57 AM