Aim

To study the basic components of house wiring, safety devices, house wiring rules as per ISI-specification and safety measures of electrical wiring.

Components of Basic Electrical Wiring

Besides safety precautions and regulations, the main thing want to familiarise the design of house wiring. It consists of three basic components:

➢ Service Entry

This refers to service wire (which brings power supply) from the main grid or pole to house and the Energy meter. The service entry is critical and there are a few things to keep in mind. First of all, make sure all service line are at least 10 feet above the ground, inaccessible from windows, and free of obstructions such as tree limbs. Besides that, make sure your service entry is properly installed so that no water can penetrate the access point or meter. Any changes or fault rectification in this area must be done by the service provider i.e, T.N.E.B.

➢ Panel Board

Panel board is the control centre for electrical wiring. It consists of Main switch and Distribution fuse board. Now-a-days new safety devices Double Pole MCB instead of Main Switch and Single Pole MCB instead of distribution fuse were used. While installing an Air conditioner, Heater, Washing machine or running wiring to a new addition, ensure electricity is switched off before starting the work, and where you install new breakers.

➢ Branch Circuits

Calculate total load of various electric points used in house, and the wiring should be carried out on distribution systems with branch circuits. Each branch circuit must have light circuits not exceeding 10 points or 800 watts, if power wiring circuit not more than 2 points and AC 1 point. This refers to isolate the areas of house from panel board. For instance, you cut power to your kitchen while the rest of the house is in operation.

EMA_English_Practical.indd 196 11/9/2020 3:56:05 PM