Assume that we hold the current carrying conductor in our right hand such that the thumb points in the direction of current flow, then the fingers encircling the conductor point in the direction of the magnetic field lines produced.

The Figure 3.28 shows the right hand rule for current carrying straight conductor and circular coil.




Figure 3.28 Right hand rule – straight conductor and circular loop

3.7.4 Maxwell's right hand cork screw rule

This rule can also be used to find the direction of the magnetic field around the current-carrying conductor. If we rotate a right-handed screw using a screw driver, then the direction of current is same as the direction in which screw advances and the direction of rotation of the screw gives the direction of the magnetic field. (Figure 3.29)






Figure 3.29 Maxwell's right hand cork screw rule

EXAMPLE 3.12

The magnetic field shown in the figure is due to the current carrying wire. In which direction does the current flow in the wire?.



Solution



Using right hand rule, current flows upwards.

UNIT-3(XII-Physics_Vol-1).indd 153 14-02-2020 20:03:28