For equilibrium of the rod,

$$mg\sin 45^\circ = IBl\cos 45^\circ$$

$$\Rightarrow I = \frac{1}{B}\frac{m}{l}g\tan 45^\circ$$

$$= \frac{0.25\,\text{kg m}^{-1}}{0.25\,T}\times 1\times 9.8\ \text{m s}^{-2}$$

$$\Rightarrow I = 9.8\,\text{A}$$

So, we need to supply current of 9.8 A to keep the metallic rod stationary.

3.10.6 Force between two long parallel current carrying conductors

Let two long straight parallel current carrying conductors separated by a distance r be kept in air medium as shown in Figure 3.53. Let I_1 and I_2 be the electric currents passing through the conductors A and B in same direction (i.e. along z - direction) respectively. The net magnetic field at a distance r due to current I_1 in conductor A is

$$\vec{B}_1 = \frac{\mu_\circ I_1}{2\pi r}(-\hat{i}) = -\frac{\mu_\circ I_1}{2\pi r}\hat{i}$$




Figure 3.53 Two long straight parallel wires

From thumb rule, the direction of magnetic field is perpendicular to the plane of the paper and inwards (arrow into the page ⊗) i.e. along negative $\hat{i}$ direction.

Let us consider a small elemental length dl in conductor B at which the magnetic field $\vec{B}_1$ is present. From equation 3.66, Lorentz force on the element dl of conductor B is

$$d\vec{F} = \left(I_2 d\vec{l}\times\vec{B}_1\right) = -I_2 dl\frac{\mu_\circ I_1}{2\pi r}(\hat{k}\times\hat{i})$$

$$= -\frac{\mu_\circ I_1 I_2 dl}{2\pi r}\hat{j}$$

Therefore the force on dl of the wire B is directed towards the conductor A. So the element of length dl in B is attracted towards the conductor A. Hence the force per unit length of the conductor B due to current in the conductor A is

$$\frac{\vec{F}}{l} = -\frac{\mu_\circ I_1 I_2}{2\pi r}\hat{j}$$

Similarly, the net magnetic induction due to current I_2 (in conductor B) at a distance r in the elemental length dl of conductor A is

$$\vec{B}_2 = \frac{\mu_\circ I_2}{2\pi r}\hat{i}$$

From the thumb rule, direction of magnetic field is perpendicular to the plane of the paper and outwards (arrow out of the page ⊙) i.e., along positive $\hat{i}$ direction. Hence, the magnetic force acting on element dl of the conductor A is

$$d\vec{F} = \left(I_1 d\vec{l}\times\vec{B}_2\right) = I_1 dl\frac{\mu_\circ I_2}{2\pi r}(\hat{k}\times\hat{i})$$

$$= \frac{\mu_\circ I_1 I_2 dl}{2\pi r}\hat{j} \qquad (3.68)$$

Therefore the force on dl of conductor A is directed towards the conductor B. So the length dl is attracted towards the conductor B as shown in Figure (3.54).

UNIT-3(XII-Physics_Vol-1).indd 178 14-02-2020 20:04:46