ii) Verification of De Morgan's second theorem

- The connections are made for LHS $\left[\overline{A.B}\right]$ of the theorem as shown in the circuit diagram using appropriate ICs.
- The output is noted and tabulated for all combinations of logical inputs of the truth table.
- The same procedure is repeated for RHS $\left[\overline{A}+\overline{B}\right]$ of the theorem.
- From the truth table, it can be shown that $\overline{A.B} = \overline{A}+\overline{B}$.

OBSERVATION

De-Morgan's first theorem

Truth Table

A	B	$\overline{A+B}$	$\overline{A}.\overline{B}$
0	0		
0	1		
1	0		
1	1		

De-Morgan's second theorem

Truth Table

A	B	$\overline{A.B}$	$\overline{A}+\overline{B}$
0	0		
0	1		
1	0		
1	1		

RESULT

De Morgan's first and second theorems are verified.

Note

The pin diagram for IC 7408, IC 7432 and IC 7404 can be taken from previous experiment

Precautions

V_{CC} and ground pins must not be interchanged while making connections. Otherwise the chip will be damaged.

For the ICs used, 5V is applied to the pin 14 while the pin 7 is connected to the ground.

XII-Physics_Vol-1) PRACTICAL.indd 317 14-02-2020 20:13:13