3.5.3 Working principle

First the percolator lid is opened, and water is poured inside, through the percolating tube. Coffee powder was poured to the required quantity in the coffee basket and the lid was closed. If the supply is given, the water in the container gets heated and the steam of the water goes towards percolating tube, and soaks the coffee powder in the basket. Now the essence of coffee water is collected from the bottom of the container through a tap. Any leakage or holes in the tube, this percolator will not function.

3.5.4 Defects, reasons and remedies of coffee percolator

Sl. No.	Defects	Reasons	Remedies
1	Supply is given, coffee percolator is not functioning	1. There may be open circuit or short circuit in the power chord.	1. Open circuit or Short circuit in the power chord should be checked before giving the supply.
		2. The supply terminals not connected with heating element.	2. Connect the terminals of the heating element correctly.
2	Getting shock while using the coffee percolator	Electric supply terminal is contacting with metal parts of the coffee percolator.	The contact of supply terminal on the metal part should be properly insulated.
3	When we switch 'ON' the supply, the fuse gets melted	Short circuit in the coffee percolator.	Short circuit should be identified and gets rectified.

3.6 Geyser

A geyser is a heating appliance which is used in the places where hot water is required. Normally tubular type of heating element is used in this appliance. Nichrome is the heating element used in all heating appliances. Due to the high resistance in the heating element, the electrical energy is converted into heat energy, and the water gets heated. Thermostat, in the appliance regulates the heat produced in it.

The geyser is available in various rating of 15, 25, 35 and 50 litres and is also available from 1000 to 5000 watts.

Construction

1. Container

Geyser is an appliance used for getting huge quantity of hot water for domestic purposes. It is cylindrical in shape and contains two containers such as

1. Inner container
2. Outer container.

Inner container is made up of brass and is coated with lead to avoid

BEE_ENG_Chapter_03.indd 47 12/27/2019 10:24:52 AM