works in the micro operating system. This method of functioning depends upon the type of clothes used and its dirty.



Fig. 4.21 **Top loading washing machine**

b) Water inlet tube time control

In this type of washing machine, a controlling device is mounted. The machine is automatically operated with the washing machine and the water is inserted into the inlet tube.

c) Water outlet tube time control

It works in two ways.

1. Drip out the washed dirty water
2. It is also used to squeeze and remove water from the cloth.

d) Water tank

This washing machine has two tanks.

1. Inner tank
2. Outer tank

Water tanks are made up of steel sheet coated with zinc to prevent corrosion inside the tank. Put the clothes in the inner tub and washing machine perform the tasks like washing, rinsing and squeezing. The inner tank contains small holes in this pot which is used for removal of dirty water. The outer tank is made up of steel and painted to protect from corrosion. In between inner and outer tank, Glass wool is provided in order to protect the hotness from the inner tank, and protect from chillness not to affect the inner tank.

e) Agitator

The agitator is a roller shaped hard plastic and is placed in the middle of the inner tank. The knife edge part of agitator makes the cloths to rotate it, in front and back with soap mixed water. This removes the dirty in the clothes.

f) Electric motor

The fractional horse power motor is used in washing machine. When the supply is given, the agitator rotates along with motor with the setting position according to the quantity of the cloth. Single phase 230-volt, 50 Hz supply is given to this motor.

g) Circuit board

The circuit board combines various electronic components. The mechanism of the machine will be set in advance according to the size and type of fabric used in the washing machine. This circuit determines the duration of washing the clothes, quantity of water, detergent quantity and time duration.

BEE_ENG_Chapter_04.indd 62 12/27/2019 10:27:23 AM