10.13 Troubleshooting, causes and remedies in the ignition system

1. Engine Misfiring

Sl.No.	Cause	Remedy
1.	Spark plug faulty	Clean, regap or replace the spark plug
2.	Loose electrical wiring	Tighten, clean the wires
3.	Late ignition timing	Correct ignition timing
4.	Wear and tear of contact breaker point	Replace
5.	Faulty ignition coil	Replace

2. Engine does not start

Sl.No.	Cause	Remedy
1.	Cable lose, corroded, open terminal	Tight, repair as needed
2.	Defective ignition switch	Replace
3.	Faulty condenser	Rectify
4.	Defective contact breaker points	Rectify
5.	Low voltage in the battery	Charge the battery

10.14 Troubleshooting, causes and remedies in Starter Motor

1. Starter motor does not start

Sl.No.	Cause	Remedy
1.	Low voltage in the battery	Charge the battery
2.	Burned coil / winding	Replace
3.	Faulty starting switch	Rectify
4.	Faulty armature	Repair or replace
5.	Dust on sleeve or pinion	Clean the parts

Student Activity

1. Students are advised to submit a detailed report based on the visit to the nearest service station to study the service of various electrical components such as a battery, ignition coil, condenser, spark plug etc.
2. Students are asked to prepare and submit a detailed report with appropriate sketches on the starting system, charging system and lighting system based on the visit to the nearest service station.

BAE_ENG_Chapter_10.indd 215 12/20/2019 1:10:29 PM