Next, build and run Edge Service (`./gradlew bootRun`). Since no downstream services are running (if they are, you should stop them), all the requests sent to them from Edge Service will result in errors. Let's see what happens if we run 21 sequential `POST` requests (`-n 21 -c 1 -m POST`) to the `/orders` endpoint. Remember that `POST` requests have no retry configuration, and `order-route` has no fallback, so the result will only be affected by the timeout and circuit breaker:

```
$ ab -n 21 -c 1 -m POST http://localhost:9000/orders
```

From the `ab` output, you can see that all the requests returned an error:

```
Complete requests: 21
Non-2xx responses: 21
```

The circuit breaker is configured to trip to the open state when at least 50% of the calls in a 20-sized time window fails. Since you have just started the application, the circuit will transition to the open state after 20 requests. In the application logs, you can analyze how the requests have been handled. All the requests failed, so the circuit breaker registers an `ERROR` event for each of them:

```
Event ERROR published: CircuitBreaker 'orderCircuitBreaker'
  recorded an error.
```

At the 20th request, a `FAILURE_RATE_EXCEEDED` event is recorded because it exceeded the failure threshold. That will result in a `STATE_TRANSITION` event that will open the circuit:

```
Event ERROR published: CircuitBreaker 'orderCircuitBreaker'
  recorded an error.
Event FAILURE_RATE_EXCEEDED published: CircuitBreaker 'orderCircuitBreaker'
  exceeded failure rate threshold.
```