```
} else {
    print "else" . PHP_EOL;
}
```

```
Output:
elseif
```

You can chain together as many `elseif` blocks as you like, but that code would grow untidy rather quickly. There is an alternative syntax for this control structure (and others) using colons…

```
if (EXPR):
    //one or more statements
elseif (EXPR):
    //one or more statements
else:
    //one or more statements
endif;
```

… but it is unusual to see it in modern PHP. The PSR-12 standard recommends that you use braces.

`switch`, `match`

An alternative to multiple `if`/`elseif` statements is the `switch`/`case` construct:

```
$var = 'foo';
switch ($var) {
    case 'bar':
        print 'bar' . PHP_EOL;
    case 'foo':
        print 'foo' . PHP_EOL;
}
```

```
Output:
foo
```