

Special offer for Digit readers

You can purchase innovative solar-powered products from Solar Spectrum Energy Systems. For more details, email mahaurja@gmail.com. Avail your special discount by mentioning this Digit article

Make a difference

Think green. Find out how in the community section of this issue

DIY



Mirolta ultra-bright LED tubelight with 144 Japanese LEDs

Solar Lantern

Model: CFL lantern

MRP: Rs. 2,500

Digit special price: Rs. 1,975

You can depend on solar powered lights when you don't have electric supply. This is a portable, lightweight, all-weather durable and easy to use lamp. This has premium quality 3Wp mono/multicrystalline silicon solar panel with high capacity 6V/4 Ah Lead Acid battery. You have the option to charge the battery either by solar panel or AC mains. Model: LED filament

MRP: Rs. 3,500

Digit special price: Rs. 2,600

This is similar to the CFL Lantern. However, you can adjust the brightness of the lantern



LED filament lantern (Patent pending)

between three levels – Bright: 6 hrs, Medium: 8 hrs and Candle light mode: 12 hrs. The product was designed and developed by Gupta's associates.

SPECIAL INSTRUCTIONS

Going by the red is positive and black is negative thumb rule will save you a lot of rework. Using a single colour wire results in a lot of confusion over connectivity, and going by past experience, seeing a component blow up is not a pleasant sight. It's not wise playing with a battery. Keep it away from inflammable substances. 6V batteries are capable of generating sufficient sparks to trigger a fire. Do not short the terminals of the battery. Similarly, the solar panel generates a DC voltage that should not be reversed. Connect the red wire to the positive of the battery and the black to the negative of the battery.

Diodes and LEDs (which are also

diodes – light emitting diodes) conduct electricity in a single direction only. They prevent reverse flow of current. For a diode or LED to conduct, its anode should be connected to a positive potential and cathode should be connected to negative. Do not connect the LEDs directly to the battery. Although it appears attractive, white LEDs are not able to withstand a potential of 6V across them. This is precisely why we connect 2 LEDs in series (to offset the potential difference of 6V evenly across LEDs and ensure safe operating point) and then connect similar LED groups in parallel (to increase brightness of our lamp). The longer terminal is anode, and the shorter terminal is cathode.

LED lamps carry a warranty of 5 years, while the solar panel carry a warranty of 10 years.

Solar Home Light Systems (SMPS Bases)

Model: Mirolta

MRP: Rs.5,500

Digit special price: Rs. 3,000.

6V / 4.5 Ah, sealed maintenance free battery

Dual-charging options (solar and mains)

Dual mode operation (High mode: 5 hrs; Normal mode: 8 hrs)

SMPS-based battery charging Operation between 50 V to 300 V AC

144 ultra-bright Japanese LEDs

Easy To Install

No Maintenance required

50,000 hrs

Warranty: LED lamp: 5 yrs, solar module: 10 yrs

Do write in and let us know if you would be interested in optimising your solar-powered device using a charge controller. **d**

There are two types of solar panels: Amorphous and polycrystalline type. Polycrystalline panels are better and longer lasting than the amorphous type. Place the panel in an area with sufficient sunlight throughout the day. Ensure, the area won't be covered with the shadow of a neighbouring building in a couple of hours. You can try placing them on the highest available point. If you are a minor, we recommend taking the help of an adult for this. Do not attempt mounting the panel in risky positions of your building/house. Consider taking professional help in case you are not able to install it. Either way, window sunshine should be sufficient to charge your battery.



Your eyeball view.
Our technology view.

Sketch your imagination

**RIGHT HERE.
RIGHT NOW.**



Design Tablet PF1209

- High 2000 lpi resolution for pin point accuracy •
- 1024 Pressure levels •
- Capture any screen with free hand notes using Annotate all •
- Major drawing, painting, CAD, Office XP & Office 2003 programs supported •



Write • Draw • Design

Also available in :
4" x 3" | 5.5" x 4" | 8" x 6"

Over 14 million iBall products sold | www.iBall.co.in

Best IT World (India) Pvt. Ltd. - Email : sales@iball.co.in
Mumbai - 022- 30815100, 6774 5100, 98207 23393, **Ahmedabad** - 079-2743 6373, **Bangalore** - 080- 41249609, **Bhubaneswar** - 0674-3297372, **Chandigarh** - 0172-5009548, **Cochin** - 0484-2324 706, **Chennai** - 044-32451506, **Dehradun** - 0135-3244481, **Guwahati** - 09435731463 / 09435041133, **Goa** - 9764211099, **Indore** - 0731-404 2509, **Jaipur** - 0141-3295690, **Kolkata** - 09830811411 / 09830113980, **New Delhi** - 09312086932, **Lucknow** - 0522-3246428, **Nagpur** - 0712-3253811, **Nashik** - 09822026887, **Pune** - 09322284377, **Patna** - 0612- 3260947, **Raipur** - 0771-3293674, **Secunderabad** - 040-2789 4847