

#define direction_a 12	Define direction pin on Arduino™ board	Motor Channel A
#define speed_a 3	Define speed pin on Arduino™ board	
#define brake_a 9	Define brake pin on Arduino™ board	
#define direction_b 13	Define direction pin on Arduino™ board	Motor Channel B
#define speed_b 11	Define speed pin on Arduino™ board	
#define brake_b 8	Define brake pin on Arduino™ board	
void setup () {		
pinMode (direction_a, OUTPUT);	Set function for direction pin	Motor Channel A
pinMode (brake_a, OUTPUT);	Set function for brake pin	
pinMode (direction_b, OUTPUT);	Set function for direction pin	Motor Channel B
pinMode (brake_b, OUTPUT);	Set function for brake pin	
}		
void loop () {		
digitalWrite (direction_a, HIGH);	Rotate motor in forward direction	Motor Channel A
digitalWrite (brake_a, LOW);	Disengage the brake	
analogWrite (speed_a, 255);	Spin the motor at full speed	
digitalWrite (direction_b, HIGH);	Rotate motor in forward direction	Motor Channel B
digitalWrite (brake_b, LOW);	Disengage the brake	
analogWrite (speed_b, 123);	Spin the motor at half speed	
delay (3000);	Rotate as above for 3 seconds	
digitalWrite (brake_a, HIGH);	Engage brake for Channel A	
digitalWrite (brake_b, HIGH);	Engage brake for Channel B	
delay (1000);	Wait for 1 second	
digitalWrite (direction_a, LOW);	Rotate motor in forward direction	Motor Channel A
digitalWrite (brake_a, LOW);	Disengage the brake	
analogWrite (speed_a, 123);	Spin the motor at half speed	
digitalWrite (direction_b, LOW);	Rotate motor in forward direction	Motor Channel B
digitalWrite (brake_b, LOW);	Disengage the brake	
analogWrite (speed_b, 255);	Spin the motor at full speed	
delay (3000);	Rotate as above for 3 seconds	
digitalWrite (brake_a, HIGH);	Engage brake for Channel A	
digitalWrite (brake_b, HIGH);	Engage brake for Channel B	
delay (1000);	Wait for 1 second and go to the beginning of loop () again to repeat same functions	
}		