

clips were also used which made the process easier. They allow you to free up your hands.

Now that we have the multimeter connected, the next step is to set the dial to the appropriate setting and measure the current. Just as measuring voltage and resistance, you must get the correct range to accurately measure current. Set up the multimeter to 200mA and make sure that the red probe is plugged into the 200mA fused port. If you suspect that your circuit will be using more than 200mA, move your probe to the 10A side since overloading the current can result in a blown fuse. You will now be able to see the current reading on the multimeter display. Multimeters actually take readings over time and display the average, so the readings might fluctuate.

Continuity

Testing the resistance between two points is known as continuity testing. If there is very low resistance between two points that are connected electrically i.e. if they are 'shorted', a sound is emitted and vice versa. This test will help you understand if two points are connected properly in a circuit. You can also test the conductivity of materials and trace where electric connections are or where the circuit is broken but should not be.



For this, set the multimeter to 'Continuity' mode. If you can't find it, look for a diode symbol or a speaker symbol. Then to test if everything is working properly, you can touch the probes together and the multimeter should emit a tone. It's always a good practice to do this since it tells you that you've attached the probes properly and that the probes are conducting properly.

Next, take a breadboard and don't power it. Use the probes to poke two separate ground pins on either the top row or the bottom row. You will hear a sound that indicates they are connected. Now, place an IC over the centre bridge. To check if your IC's pins have made contact with the underlying