

**XOR**

**Logical XOR – MySQL XOR operator takes two expressions and then returns TRUE when one or the other but not both are TRUE.**

## MySQL AND

AND Logical operator in MySQL compares two given expression and returns the TRUE if both the given expression are TRUE.

**Syntax:** `AND, &&`

AND Operator returns 1 if all operands are nonzero and not NULL, AND Operator returns 0 if one or more operands are 0. Otherwise, NULL is returned.

**Example:**

In the given example we are taking operands (3 and 3) that are non-zero. So as per the AND Logical operator, both of these are not Null and it will return 1.

```
SELECT 3 && 3;
```

Output will take the form as:

```
MySQL> SELECT 3 && 3;
```

```
+-----+
```

```
| 3 && 3 |
```

```
+-----+
```

```
|      1 |
```

```
+-----+
```

```
1 row in set (0.00 sec)
```

## MySQL OR

OR Logical Operator in MySQL compares two expressions in a given condition and returns TRUE if either of the expression is TRUE.

**Syntax:** `OR, | |`

OR operator will return 1 in case both operands have non-NULL values and one of them is non-zero, OR operator will return 0 in case both operands have non-NULL values and one of them is zero, OR operator will return NULL in case one of the operands is NULL and other is zero, OR operator will return 1 in case one is NULL and other is a nonzero, OR operator will return NULL when both the operands are NULL.

**Example:**

In the given example both the operands are non-NULL values and one of them is non-zero so the Logical OR operator returns value 1.

```
SELECT 3 | | 3;
```

The output will take the form as: