

2.2.1 AMIBIOS (American Megatrends Inc.)

One beep: RAM failure

Problem: Motherboard problem or failed RAM.

Solution: Troubleshoot the motherboard and/or the RAM.

Two beeps: Parity Circuit Failure

Problem: Motherboard problem or failed RAM.

Solution: Troubleshoot the motherboard and/or the RAM.

Three beeps: Base 64K RAM failure

Problem: There is a failure within the first 64K of memory.

Solution: Troubleshoot the motherboard and/or the RAM.

Four beeps: System Timer Failure

Problem: One or more of the system timers on the motherboard has failed; usually indicates motherboard failure.

Solution: Troubleshoot the motherboard. You may need to replace it.

Five beeps: Processor Failure

Problem: The processor is generating an error condition. This does not mean that the processor is not working—with a dead processor, the computer won't boot at all.

Solution: Check if the processor is overheating, and whether it is set correctly on the motherboard. Troubleshoot the motherboard.

Six beeps: Keyboard controller or gate A20 failure

Problem: Keyboard, keyboard controller or motherboard error.

Solution: Check if the keyboard is connected properly. Use another keyboard to see if the problem persists. If it does, look for the keyboard controller chip on the motherboard and see if it is seated properly and that it is not damaged. If the problem continues, troubleshoot the motherboard.

Seven beeps: Virtual mode exception error

Problem: This error is reported when testing the processor's virtual mode.

Solution: Troubleshoot the motherboard/processor. Verify that