

```
        echo "x is NOT bigger than y";  
    }  
?>
```

elseif/else if: It is a combination of 'if' and 'else' Control Structure. If the 'if' Control Structure returns a 'false' value, then a different statement is executed by using the 'else' Control Structure'.

Example:

```
<?php  
if ($x > $y) {  
    echo "x is bigger than y";  
} elseif ($x == $y) {  
    echo "x is equal to y";  
} else {  
    echo "x is smaller than y";  
}  
?>
```

“Alternative syntax for control structures: There are some alternative syntax for some control structures like, 'if', 'while', 'for', 'foreach' and 'switch'. It changes the opening brace to a colon sign (:) and closing brace to endif:, endwhile:, endfor:, endforeach:, or endswitch.

Example:

```
<?php  
if ($x == 6):  
    echo "x equals 6";  
    echo "...";  
elseif ($x == 7):  
    echo "x equals 7";  
    echo "!!!";  
else:  
    echo "x is neither 6 nor 7";  
endif;  
?>
```

while: The 'while' Control Structure executes the nested statements repetitively until the 'while' statement returns a false value. The syntax of 'while' control structure is as follows:

```
while (expr)  
statement
```