

```
if ((a%2) == 0) {  
    Output_high(pin_C1);  
}
```

The if...then...else construct

```
if (logical expression) {  
    ...if statements...  
}  
else {  
    ...else statements...  
}
```

If the logical expression is true then evaluate the "if" statements between the braces, otherwise execute the "else" statements. The following code decides if a number is even or odd.

```
if ((a%2) == 0) {  
    Output_high(pin_C1);  
}  
else {  
    Output_low(pin_C1);  
}
```

The while loop

```
while (logical expression) {  
    ...statements...  
}
```

While the logical expression is true, the statements (of which there is an arbitrary number) between the braces is executed. The following code cycles through the even numbers from 0 to 9 (the variables must have been declared elsewhere in the program).

```
a=0;  
while (a<10) {  
    ...statements...  
    a=a+2;  
}
```