



Benchmark Power MOSFETs for High Performance Applications

Benchmark Point of Load: VRM, Buck Regulation

Part Number	V_{DS} (V)	I_D (A)	$R_{DS(on)}$ Max $V_{GS}=10V$ (m Ω)	Q_g (nC)	Package
IRFH7923PBF	30	15	8.7	8.7	PQFN
IRFH7932PBF	30	25	3.3	34	PQFN
IRF8721PBF	30	14	8.5	8.3	SO-8
IRF8788PBF	30	24	2.8	44	SO-8
IRLR8721PBF	30	65	8.4	8.5	D-PAK
IRLR8743PBF	30	160	3.1	39	D-PAK

IR's latest MOSFETs offer benchmark performance and are tailored for DC/DC conversion, AC/DC synchronous rectification, and Industrial Battery applications such as E-Bike and UPS systems.

IR's latest Trench technology in a wide range of packages up to 250V enables low $R_{DS(on)}$ low gate charge, and high switching capability for today's demanding designs.

Benchmark Power Supply: Synchronous Rectification

Part Number	V_{DS} (V)	I_D (A)	$R_{DS(on)}$ Max $V_{GS}=10V$ (m Ω)	Q_g (nC)	Package
IRF2804(S)PBF	40	270	2.0	160	TO-220(D ⁺ -PAK)
IRFB(S)3206PBF	60	219	3.0	120	TO-220(D ⁺ -PAK)
IRFB3077PBF	75	210	3.3	160	TO-220
IRLB4110PBF	100	180	4.5	150	TO-220
IRF7853PBF	100	8.3	18	28	SO-8

www.irf.com

Benchmark Industrial: Industrial Battery, UPS

Part Number	V_{DS} (V)	I_D (A)	$R_{DS(on)}$ Max $V_{GS}=10V$ (m Ω)	Q_g (nC)	Package
IRF3205Z(S)PBF	55	110	6.5	76	TO-220(D ⁺ -PAK)
IRFB(S)3806PBF	60	43	15.8	22	TO-220(D ⁺ -PAK)
IRF1018E(S)PBF	60	79	8.4	46	TO-220(D ⁺ -PAK)
IRFB(S)3607PBF	75	80	9.0	56	TO-220(D ⁺ -PAK)
IRFB(S)33072PBF	75	120	5.8	79	TO-220(D ⁺ -PAK)

**Your FIRST CHOICE
for Performance**

For any enquiry, please contact us using our "Customer Relationship Management (CRM) System" on www.irf-asia.com/contact or www.irf.com.cn/contact.

International
IRF Rectifier
THE POWER MANAGEMENT LEADER