

Fig. 3: Circuit for LED pendulum




Fig. 4: Arrangement of LEDs on LED pendulum

mode and its clock pulse at pin 3 is fed to clock pin 14 of decade counter 4017 (IC3). The outputs of IC3 are connected with the help of switching diode 1N4148 such that the six LEDs (LED3 through LED8) flash in sequence in one direction first and then in reverse sequence. The speed of flashing of LEDs can be adjusted with the help of 10-kilo-ohm preset VR2. Capacitor C6 (6.8nF) and resistor R11 (100-kilo-

ohm) are used to reset the decade counter.

Assemble the circuit on a general-purpose PCB and enclose in a suitable cabinet. Mount the LEDs either in 'V' shape or 'U' shape on the front panel of the cabinet (as shown in Fig. 4). ●

Tell Me More About Advertising Opportunities in EFY Magazine

I am aware that EFY Magazine presents umpteen advertising opportunities. I too would like to explore the various options available for my organisation, so that I can help it grow in terms of sales and brand presence. My details are mentioned below:

Name _____
 Organisation _____
 Designation _____
 Address _____
 City _____ Pincode _____
 Phone _____ Fax _____
 E-mail _____

I would like to have a one-to-one meeting

- ☐ I would like to have a one-to-one meeting with someone from the EFY team.
☐ Please send me your marketing kit containing all necessary details.

Please mail/fax this form to:



EFY Enterprises Pvt Ltd

D-87/1, Okhla Industrial Area, Phase-I, New Delhi 110020

Tel: 011-26810601/2/3; Fax: 011-26817563

Email: efymkt@efyindia.com; Website: www.efyindia.com