

Database1.java file, which is located under 'Rahul' folder, requires the IP address of the server. So open the ConnectDatabase1.java source file and replace 'localhost' with the IP address of the server wherever 'localhost' appears. Save the file and close it.

5. Provide an appropriate path for JDK as mentioned in Step 4 under the previous sub-heading, and compile

both ConnectDatabase1.java and ClientOnline.java programs.

6. Run the ClientOnline.java program. You will see the program output as shown in Fig. 1. Click the appropriate button to proceed for the online exams.

EFY-CD. All the relevant files and source codes of this article have been included in this month's EFY-CD.

SERVERONLINE.JAVA

```
import java.net.*;
import java.io.*;
import java.sql.*;

public class ServerOnline {
    public static void main(String
args[]) {
        try {
            DriverManager.registerDriver(new
sun.jdbc.odbc.JdbcOdbcDriver());
        } catch (Exception e) {
            System.out.println("Error oc-
cured : "+e.getMessage());
        }
        new ServerClass();
    }
}

class ServerClass implements Runna-
ble {
    Thread t;
    ServerSocket echoServer = null;
    Socket clientSocket = null;

    ServerClass() {
        try {
            echoServer = new ServerSock-
et(1111);
        } catch (IOException e) {
            System.out.println("Could not
start server." + e);
            System.exit(1);
        }

        t = new Thread(this);
        System.out.println("Server started
!!!");
        t.start();

        public void run() {
            try {
                while(true) {
                    clientSocket = echoServer.
accept();
                    connection con = new connec-
tion(clientSocket);
                }
            } catch (IOException e) {
                System.err.println("Not listen-
ing." + e);
                System.exit(1);
            }
        }
    }

    class connection implements Runnable {
        Thread t;
        String tableName = ""; //this gets
the name of the tablename from where
the question and options are to be re-
trieved
        String requestQuestion = "";

        BufferedReader is = null;
        PrintStream os = null;
        Socket clientSocket = null;

        Connection conn;
        Statement stmt;

        String chapterSelected = "", pass;

        public connection(Socket client-
Socket) {
            this.clientSocket = clientSocket;
        }

        try {
            is = new BufferedReader(new
InputStreamReader(clientSocket.getInput-
Stream()));
            os = new
PrintStream(clientSocket.getOutputStream());
        } catch (IOException e) {
            try {
                clientSocket.close();
            } catch (Exception ex) {}
            System.err.println("Unable to
setup stream "+e);
            return;
        }

        t = new Thread(this, "");
        t.start();

        public void run() {
            try {
                conn = DriverManager.
getConnection("jdbc:odbc:OnlineExams");
                stmt = conn.createStatement(Resu-
ltSet.TYPE_SCROLL_INSENSITIVE, ResultSet.
CONCUR_READ_ONLY);

            } catch (Exception e) {
                System.out.println("Error oc-
cured : "+e.getMessage());
            }

            try {
                pass = is.readLine();

                if (pass.equals("1")) {
                    tableName =
is.readLine(); //subject-
Selected
                    tableName +=
is.readLine(); //classSe-
lected

                    ResultSet rset = stmt.
executeQuery("Select * from "+tableName-
);
                    rset.last();
                    os.println(rset.get-
String(1)); //lastSNo

                    rset = stmt.
executeQuery("Select * from "+tableNa-
```



**when quality can't be
compromised, turn to
Gunze USA**

We're one of the world's
largest suppliers of analog-
resistive touch panels, enabling
the highest LCD visibility, providing
exceptional durability and pinpoint
accuracy. Our touch screens
are used by

discerning OEMs and companies
worldwide that value technology
leadership, customer service and
quality.

Gunze USA-world leader in
analog-resistive touch panels.

contact in india

M S ELECTRONICS MARKETING (P) LTD.
DISTRIBUTORS FOR GUNZE ELECTRONICS USA CORPORATION

3-4-142/7, GROUND FLOOR
GOUTHAMI APARTMENTS
BARKATHUPURA
HYDERABAD-500027
A.P. INDIA

PHONES- +9140-64529593
+9140-27560158
FAX +9140-66630594

e-mail:sales@mselectronicscompany.com
www.mselectronicscompany.com