



Benchmark Power MOSFETs for High Performance Applications

Benchmark Point of Load: VRM, Buck Regulation

Part Number	V_{DS} (V)	I_D (A)	$R_{DS(on)}$ Max $V_{GS}=10V$ (m Ω)	Q_g (nC)	Package
IRFH5250	25	45	1.2	52	PDFN5x6
IRFH5250D	25	40	1.4	83	PDFN5x6
IRFH5255	25	15	6.0	7	PDFN5x6
IRFHM831	30	14	7.8	7.3	PDFN3x3
IRFHM830	30	21	3.8	15	PDFN3x3
IRFHM830D	30	20	4.3	13	PDFN3x3
IRFH5302	30	32	2.1	4.8	PDFN5x6
IRFH5302D	30	29	2.5	26	PDFN5x6
IRFH5303	30	23	4.2	15	PDFN5x6
IRFH5304	30	22	4.5	16	PDFN5x6
IRFH5306	30	15	8.1	7.8	PDFN5x6

IR's latest MOSFETs offer benchmark performance and are tailored for DC/DC conversion, AC/DC synchronous rectification, and Industrial Battery applications such as E-Bike and UPS systems.

IR's latest Trench technology in a wide range of packages up to 250V enables low $R_{DS(on)}$, low gate charge, and high switching capability for today's demanding designs.


Benchmark Power Supply: Synchronous Rectification

Part Number	V_{DS} (V)	I_D (A)	$R_{DS(on)}$ Max $V_{GS}=10V$ (m Ω)	Q_g (nC)	Package
IRFB(S)3004PBF	40	330	1.75	160	TO-220(D ² -PAK)
IRFH5004	40	100	2.6	73	PDFN5x6
IRFB(S)3006PBF	60	270	2.5	200	TO-220(D ² -PAK)
IRFH5006	60	100	4.1	67	PDFN5x6
IRFB307PBF	75	210	3.3	160	TO-220
IRFH5007	75	100	5.9	65	PDFN5x6
IRFB4110PBF	100	180	4.5	150	TO-220
IRF7853PBF	100	8.3	18	28	SO-8
IRFH5010	100	100	9.0	65	PDFN5x6
IRFH5015	150	56	31.0	33	PDFN5x6
IRFH5020	200	43	55.0	36	PDFN5x6
IRFH5025	250	32	100.0	37	PDFN5x6

Benchmark Industrial: Industrial Battery, UPS

Part Number	V_{DS} (V)	I_D (A)	$R_{DS(on)}$ Max $V_{GS}=10V$ (m Ω)	Q_g (nC)	Package
IRF3205Z(S)PBF	55	110	6.5	76	TO-220(D ² -PAK)
IRFB(S)3806PBF	60	43	15.8	22	TO-220(D ² -PAK)
IRF1018E(S)PBF	60	79	8.4	46	TO-220(D ² -PAK)
IRFB(S)3807PBF	75	80	9.0	56	TO-220(D ² -PAK)
IRFB(S)3307ZPBF	75	120	5.8	79	TO-220(D ² -PAK)

Your FIRST CHOICE for Performance



For more information, please visit us at www.irf.com or www.irf.com.cn

International
IR Rectifier
THE POWER MANAGEMENT LEADER