




Fig. 2: An actual-size, single-side PCB for USA-style twin horn




Fig. 3: Component layout of the PCB

second astable multivibrator is built around resistor R3, preset VR2, resistor R4 and capacitor C4. Any of the three mentioned sets of frequencies can be selected using VR1 and VR2.

The 10W audio amplifier circuit built around IC2 provides high output current, low harmonics and cross-over distortion. The 4.6W dual-audio amplifier circuit built around IC3 provides outputs for the two horns.

The outputs of both the astable multivibrators are either combined

on PCB, enclose it in a suitable plastic case. The PCB has three parts: dual-frequency generator, 10W audio power amplifier and 4.6W dual-audio power amplifier.

If you want mono output, connect CON1 and CON2, which will activate speaker LS1. If you want stereo output, connect CON1 and CON3, which will activate speakers LS2 and LS3. Use a suitable cabinet to house the speakers. ●

The author is a regular contributor to EBY

and passed onto the 10W audio power amplifier or separately passed onto the 4.6W dual-audio power amplifier. When you connect CON1 and CON2, the 10W audio power amplifier gets connected to the frequency generator section and produces sound corresponding to the mix of both the frequencies through speaker LS1. Similarly, when you connect CON1 and CON3, the 4.6W dual-audio power amplifier gets connected to the frequency generator and produces dual sound through speakers LS2 and LS3. Power supply is generated from the 12V car/bike battery.

Construction and testing

An actual-size, single-side PCB for the twin horn is shown in Fig. 2 and its component layout in Fig. 3. After assembling the circuit

www.kitsnspares.com

**electronics
engineering**

Can Be Fun & Exciting


(NEW ARRIVALS)

Noise
Level alarm



Rs 250/-

Moisture Monitor For Plants



Rs 250/-

Clap controlled Switch



Rs 275/-

To BUY Call: 08800100761 or Visit
www.kitsnspares.com/picboard to BUY ONLINE!

Kits'n'Spares.com
For the 'engineer' in you

D-88/3, Okhla Industrial Area, Phase 1, New Delhi 110020
Phone: 011-26371661 | E-Mail: info@kitsnspares.com
| Website: www.kitsnspares.com