

***Want to experiment with PV Solar operated Equipment
inside your lab even at night?***

Several IITs and other customers in the world use

DE PV SOLAR PANEL SIMULATOR

DEDL SAS120/10 Modular Solar Array Simulator is a programmable DC Power Source that behaves exactly like a PV Solar Panel and simulates output characteristics of a solar array. Like any Photo-Voltaic Panel, SAS120/10 is a current source with very low output capacitance and is capable of simulating I-V curve of solar arrays at different temperature, irradiance etc like a PV source.

SAS120/10 is supported with intelligent front-end software that simulates any curve with Voc, Isc, Vmp, Imp parameters or manually programmed points and its USB output allows graphical display of curves on any laptop or a computer screen. It provides simulation of Voc (open circuit voltage) up to 121V and Isc (short circuit current) up to 10.5A. SAS120/10 is highly stable and is designed for a fast transient response design, which are both advantageous for MPPT performance evaluation on PV inverter devices.

Features:

- Accurate simulation of any PV Solar Panel
- Fast I-V curve change and fast recovery switching time
- Easy to simulate temp and irradiance as under open sky conditions
- Real time analysis of PV inverters and MPPT tracking via soft panel testing MPPT tracking efficiency
- Captured data from SAS120/10 displayed on your laptop/ tabletop computer
- Four point simulation based on reference parameters
- Facility to enter user defined curve manually V-I/P-V curve display on your soft panel
- LAN, USB, and GPIB interfaces standard
- Extremely useful in mass production and problem debug scenarios

Specifications

Input Line voltage	95 to 264VAC, 45-63Hz
Output Ratings (Maximum Power)	1200
Maximum Voltage Point (Vmp)	121V
Maximum open Circuit Voltage (Voc)	120V
Maximum short circuit Current (Isc)	10.5
Maximum Circuit Point (Imp)	10A
Minimum Impedance	1Ω
(DV/VI)D Voltage	0-120V
Current	0-10A
Operating Temp	0-50°C
Output Voltage Ripple & Noise	20mV P-P
Programming Accuracy	
Voltage	0.2% of F.S. ± 1lsb
Current	0.5% of F.S. ± 1lsb
Read back Accuracy	
Voltage	0.2% of F.S
Current	0.2% of F.S
Load Regulation	
Constant voltage	0.1%
Line Regulation	0.1%

**For full details about SAS120/10 please go to
<http://www.dedl.co.in/sas.html>**



Deodhar Electro Design Pvt. Ltd.

81, SDF III, SEEPZ, Andheri (East), Mumbai 400 096, INDIA

Tel : +91 22 2829 0059 Fax : +91 22 2829 0470 E-Mail : info@dedl.co.in