



Fig. 5: Enclosure of video switcher

advances to the third count, that output passes through switch S1 to reset IC3. Decade counter starts from initial stage and activates the video signal of first camera. The sequence would be Video1, Video2, then back to Video1. Closing switch S3 or S4 of DIP switch instead of switch S2 will let the video switcher cycle through three or four cameras, respectively.

Clock pulses for the counter are

to clock input pin 14 of IC3.

The 230V, 50Hz AC mains is stepped down by transformer X1 to deliver a secondary output of 15V, 500mA. The transformer output is rectified by a full-wave rectifier comprising diodes D1 through D4, filtered by capacitor C1 and regulated by IC 7812 (IC1), which provides a 12V DC regulated output. Capacitor C2 bypasses any ripple present in regulated power

supply.

Construction. An actual-size, single-side PCB for video switcher is shown in Fig. 3 and its component layout in Fig. 4. Because of the high-frequency video signals involved, the video switcher should be built on a printed circuit board (PCB) only.

Once the components and connectors are soldered in place, the LEDs, potentiometer and DIP switch are extended through wires to the front panel of the enclosure (shown in Fig. 5). Power the transformer X1 with AC mains by closing switch S5 and measure the voltage across C2, which should be +12 volts. To select two cameras, close S2; for three and four cameras, close S3 and S4, respectively. Only one switch should be used at a time. The order of cameras is indicated by the LEDs and it should cycle from 1 through 4 and repeat. Video signals are connected with BNC connector. ●

Spanning The Height Of Heights

**Let Us Get
Ahead Together**



Tell Me More About Advertising Opportunities in EFY Magazine

I am aware that EFY Magazine presents umpteen advertising opportunities. I too would like to explore the various options available for my organisation, so that I can help it grow in terms of sales and brand presence. My details are mentioned below:

Name _____
Organisation _____
Designation _____
Address _____
City _____ Pincode _____
Phone _____ Fax _____
E-mail _____

I would like to have a one-to-one meeting

- ☐ I would like to have a one-to-one meeting with someone from the EFY team.
☐ Please send me your marketing kit containing all necessary details.

Please mail/fax this form to:



EFY Enterprises Pvt Ltd

D-87/1, Okhla Industrial Area, Phase-I, New Delhi 110020

Tel: 011-26810601/2/3; Fax: 011-26817563

Email: eflymkt@efyindia.com; Website: www.efyindia.com