

Fig. 2: Actual-size PCB pattern of the audio noise limiter




Fig. 3: Component layout of the PCB

tween C3 and pin 2 of TL072, audio gain will be $R3/R7 = 470k/4.7k = 100$ or 20dB.

The circuit is not designed for use with mobile phones. It is designed for use in SW and HAM receivers, and that too only for voice. It is basically a low-pass filter that filters out background noise and makes the speech more intelligible since human speech falls mostly in

the range of 300Hz to 3.5kHz.

Connect JACK1 to audio output of a SW receiver and JACK2 to any audio amplifier circuit. Noise is reduced due to the active low-pass filter formed around the op-amp. It attenuates all frequencies above 5kHz.

Construction and testing

An actual-size, single-side PCB for

the audio noise limiter is shown in Fig. 2 and its component layout in Fig. 3. After assembling the circuit on the PCB, enclose it in a suitable plastic box.

Keep all leads as short as possible. Connect the SW radio receiver output to JACK1 and output JACK2 to an amplifier. VR1 is for volume control. 12V regulated power supply is recommended.

JACK1 and JACK2 may be fixed on the rear side, and switch S1 and VR1 can be mounted on the front side of the box. **EFY**



Joy Mukherji is an electronics hobbyist and a small business owner in New York, USA, and Lucknow, India. His interests include designing radio-frequency circuits

www.stocko-contact.com



THE BEST CONNECTOR SYSTEMS FOR HOME APPLIANCES, AUTOMOTIVES AND HVAC


Made in Germany

- IDC Tools and Machines
- Insulation Displacement connectors

- Multiple connector systems in various pitches
- Crimp contacts in several material with different plating







STOCKO CONTACT GmbH. World's leading manufacturer of Crimp and Insulation Displacement Connector (IDC) systems. **STOCKO CONTACT GmbH** boasts of an in-house Machine Department with Hand Operated Tools, Semi Automatic as well as Fully Automatic Machines. **STOCKO** parts are widely used in Automobile, HVAC and Home Appliances Industry. In India, already 4 major projects running with Stocko parts.

Applications:

- Stoves
- Lighting system
- Air Conditioners
- Refrigerators
- Washing Machines
- HVAC Industry

Advantages:

- Saves Time
- Saves System cost
- Saves Labor
- Secure & Long lasting connections

Do visit us to explore the world of German made Crimp, IDC and Terminating Machines to provide you the best solution for your wire harness.

To Set Up a B2B meeting, feel free to contact us at sales@eurocontrols.com or Contact Our Office: +91 0202 546 5915 and NACHIKET: +91 8600 182 797

We are participating at  in Bangalore Visit us from 21-23 Sept. 2016



AURO CONTROLS PRIVATE LIMITED
ISO 9001:2008 COMPANY
Florina Apts., 6th Floor, S.No. 2/1/7, Erandwane, Off. Karve Road, Pune 411 004, India. Tel.: 020-25465915, Nachiket: +91-8600182797

AUTHORIZED DISTRIBUTORS IN INDIA, SRI LANKA AND UAE
www.aurocontrols.com