


AC-DC LED Driver




	MIP5530MDSU	MIP5540MSSCF
Package	TO-220PD7	DIP7-A1
Drain Breakdown Voltage	700V	400V
Power MOS ON state resistance	3.5Ω typ.	3.7Ω typ.
Power Factor Correction Circuit	Yes (PFC=0.9)	Yes (PFC=0.9)
Dimmer function	Triac Dimmer	Possible
	PWM Dimmer	Possible
Output current	Peak Current Limit	1.5A (Max)
	Average current	< 700mA
Protections	Over Temp. Pro	Over Temp. Pro.
	LED short Pro	LED short Pro.
Input Voltage	Non-Isolated	AC100V ~ 240V
	Isolated	AC100V ~ 240V
Power Supply Voltage	Vin detection function	> DC24V
		> DC24V



LED Driver Solutions Ideas for Light

Part Number	AN30888A	AN30888B
Type of DCDC	Buck, Boost, Buck-Boost	
Operating Input Voltage	3V to 20V	3V to 15V
Low standby current	Lower than 10 μA	
Operating Quiescent Current	Lower than 1 mA	
Under-Voltage Lock Out	2.1V +/- 0.2V	
Over Voltage Protection	Externally configurable	
Dimming	a) Voltage Feedback [2 levels] b) PWM Based (< 1 kHz)	
Efficiency	Up to 92%	
Switching Frequency	1 MHz	
Output Current	Up to Few Amperes [External N-MOSFET]	
Output Boost Voltage	Up to 35 V	
LED Drive Capability	Up to 10 Power LEDs in series	
Package	SSOP - 16 pins / QFN - 16 Pins	

DC-DC LED Driver



Semiconductor Company, Panasonic Corporation

<http://www.semicon.panasonic.co.jp/en/>

For more information, please email us at semicon.enquiry@sg.panasonic.com