



Introducing 40 V – 250 V MOSFETs in High Current Package

Offering Optimized Performance and Cost for a Given Application

Standard Gate Drive

Part Number	Package	Voltage	Current	$R_{DS(on)}$ Max. @10V	Q_g Typ @10V
IRFH5004TRPBF	PQFN 5x6mm	40 V	100A	2.6 m Ω	73 nC
IRFH5006TRPBF	PQFN 5x6mm	60 V	100A	4.1 m Ω	67 nC
IRFH5106TRPBF	PQFN 5x6mm	60 V	100A	5.6 m Ω	50 nC
IRFH5206TRPBF	PQFN 5x6mm	60 V	98A	6.7 m Ω	40 nC
IRFH5406TRPBF	PQFN 5x6mm	60 V	40A	14.4 m Ω	23 nC
IRFH5007TRPBF	PQFN 5x6mm	75 V	100A	5.9 m Ω	65 nC
IRFH5207TRPBF	PQFN 5x6mm	75 V	71A	9.6 m Ω	39 nC
IRFH5010TRPBF	PQFN 5x6mm	100 V	100A	9.0 m Ω	65 nC
IRFH5110TRPBF	PQFN 5x6mm	100 V	63A	12.4 m Ω	48 nC
IRFH5210TRPBF	PQFN 5x6mm	100 V	55A	14.9 m Ω	39 nC
IRFH5015TRPBF	PQFN 5x6mm	150 V	56A	31 m Ω	33 nC
IRFH5020TRPBF	PQFN 5x6mm	200 V	41A	59 m Ω	36 nC
IRFH5025TRPBF	PQFN 5x6mm	250 V	32A	100 m Ω	37 nC

Logic Level Gate Drive

Part Number	Package	Voltage	Current	$R_{DS(on)}$ Max. @4.5V	Q_g Typ @4.5V
IRLH5034TRPBF	PQFN 5x6mm	40 V	100A	2.4 m Ω	43 nC
IRLH5036TRPBF	PQFN 5x6mm	60 V	100A	4.4 m Ω	44 nC
IRLH5030TRPBF	PQFN 5x6mm	100 V	100A	9.0 m Ω	44 nC

Features

- Low thermal resistance to PCB (down to <0.5°C/W)
- High Current Package – up to 100A continuous
- 100% RG tested
- Low profile (<0.9 mm)
- Industry-standard pinout
- Compatible with existing surface mount techniques
- RoHS compliant containing no lead, no bromide and no halogen
- MSL1, industrial qualification

The IR Advantage

- Increased power density
- Increased reliability
- Multi-vendor compatibility
- Easier manufacturing
- Environmentally friendlier

For more information, please visit us at www.irf.com or www.irf.com.cn.

International
IR Rectifier
THE POWER MANAGEMENT LEADER