



Benchmark Power MOSFETs for High Performance Applications

Benchmark Point of Load: VRM, Buck Regulation

Part Number	V_{DS} (V)	I_D (A)	$R_{DS(on)}$ Max $V_{GS}=10V$ (m Ω)	Q_g (nC)	Package
IRFH5301	30	35	1.9	37	PQFN5x6
IRFH5302	30	32	2.1	4.8	PQFN5x6
IRFHM831	30	14	7.8	7.3	PQFN3x3
IRFHM830	30	21	3.8	15	PQFN3x3
IRFHM830D	30	20	4.3	13	PQFN3x3
IRF8721PBF	30	14	8.5	8.3	SO-8
IRF8788PBF	30	24	2.8	44	SO-8

IR's latest MOSFETs offer benchmark performance and are tailored for DC/DC conversion, AC/DC synchronous rectification, and Industrial Battery applications such as E-Bike and UPS systems.

IR's latest Trench technology in a wide range of packages up to 250V enables low $R_{DS(on)}$, low gate charge, and high switching capability for today's demanding designs.

Benchmark Power Supply: Synchronous Rectification

Part Number	V_{DS} (V)	I_D (A)	$R_{DS(on)}$ Max $V_{GS}=10V$ (m Ω)	Q_g (nC)	Package
IRFBS13004PBF	40	330	1.75	160	TO-220(D ⁺ -PAK)
IRFH5004	40	100	2.6	73	PQFN5x6
IRFBS13006PBF	60	270	2.5	200	TO-220(D ⁺ -PAK)
IRFH5006	60	100	4.1	67	PQFN5x6
IRFBS3077PBF	75	210	3.3	160	TO-220
IRFH5007	75	100	5.9	65	PQFN5x6
IRFBS4110PBF	100	180	4.5	150	TO-220
IRF7853PBF	100	8.3	18	28	SO-8
IRFH5010	100	100	9.0	65	PQFN5x6
IRFH5015	150	56	31.0	33	PQFN5x6
IRFH5020	200	43	55.0	36	PQFN5x6
IRFH5025	250	32	100.0	37	PQFN5x6

**Your FIRST CHOICE
for Performance**

Benchmark Industrial: Industrial Battery, UPS

Part Number	V_{DS} (V)	I_D (A)	$R_{DS(on)}$ Max $V_{GS}=10V$ (m Ω)	Q_g (nC)	Package
IRF3205Z(S)PBF	55	110	6.5	76	TO-220(D ⁺ -PAK)
IRFBS13806PBF	60	43	15.8	22	TO-220(D ⁺ -PAK)
IRF1018E(S)PBF	60	79	8.4	46	TO-220(D ⁺ -PAK)
IRFBS13867PBF	75	80	9.0	56	TO-220(D ⁺ -PAK)
IRFBS133072PBF	75	120	5.8	79	TO-220(D ⁺ -PAK)

For more information, please visit us at www.irf.com or www.irf.com.cn.

International
IOR Rectifier
THE POWER MANAGEMENT LEADER