

PQFN 2x2 Dual

up to 2 A

SOT-23

up to 4 A

TSOP-6

up to 7 A

PQFN 2x2

up to 10 A

Extend Battery Life With IR's Benchmark MOSFETs

Small Power MOSFETs Designed for Handheld Devices

Gate Drive - 4.5V Optimized, 2.5V Capable, 12V Maximum

BV _{DSS}	Package	Max. R _{DS(on)} @		Part Numbers
		4.5V (mΩ)	2.5V (mΩ)	
-20V	PQFN 2x2	31	53	IRLHS2242
	SOT-23	54	95	IRLML2244
20V	PQFN 2x2	11.7	15.5	IRLHS6242
	SOT-23	21	27	IRLML6244
	Dual PQFN 2x2	45	62	IRLHS6276
30V	PQFN 2x2	16	20	IRLHS6342
	TSOP-6	17.5	22	IRLTS6342
	SOT-23	29	37	IRLML6344
	Dual PQFN 2x2	63	82	IRLHS6376

Gate Drive - 10V Optimized, 4.5V Capable, 20V maximum

BV _{DSS}	Package	Max. R _{DS(on)} @		Part Numbers
		10V (mΩ)	4.5V (mΩ)	
-30V	PQFN 2x2	37	60	IRFHS9301
	SOT-23	64	103	IRLML9301
	Dual PQFN 2x2	170	290	IRFHS9351
25V	PQFN 2x2	13	21	IRFHS8242
	SOT-23	24	41	IRFML8244
30V	PQFN 2x2	16	25	IRFHS8342
	TSOP-6	19	29	IRFHS8342
	SOT-23	27	40	IRLML0030

Features

- Available in both N & P Channel for simple design
- Latest silicon technology offering low R_{DS(on)} for increased battery life
- 2.5V drive capable available for 1-cell Li-Ion Battery Applications
- PQFN package offers high power density reducing system size

Applications

- DC Load Switch
- Battery Protection
- DC-DC Converter
- Screen Backlight Boost Converter

Your **FIRST CHOICE**
for Performance

for more information, please visit us at www.irf.com or www.irf.com.cn

International
IR Rectifier
THE POWER MANAGEMENT LEADER