

```

11  When the limit is reached you'll see the notification on the UI in the Device Timeline section
12  The maximum description length for the event is 300 chars
13  * =====/
14  #define BLYNK_TEMPLATE_ID "TMPLGJA9F1s3"
15  #define BLYNK_TEMPLATE_NAME "IoT Based Fall Detection"
16  #define BLYNK_AUTH_TOKEN "lcEfKwsoa_NlCfNm3Wgomj4AL2f77sdsadp"
17
18  #define BLYNK_PRINT Serial
19  #include <WiFi.h>
20  #include <WiFiClient.h>
21  #include <BlynkSimpleEsp32.h>
22  #include <Adafruit_MPU6050.h>
23  #include <Adafruit_Sensor.h>
24  #include <Wire.h>
25
26  Adafruit_MPU6050 mpu;
27
28  char auth[] = BLYNK_AUTH_TOKEN;
29
30  char ssid[] = "MGM";
31  char pass[] = "2291yogi";
32
33  BlynkTimer timer;

```

Fig. 5: code snippet setting Wi-Fi and Blynk token

```

-
6  Adafruit_MPU6050 mpu;
7
8  char auth[] = BLYNK_AUTH_TOKEN;
9
10 char ssid[] = "MGM";
11 char pass[] = "2291yogi";
12
13 BlynkTimer timer;
14

```

Fig. 6: Code snippet

```

void sendSensor()
{
  if(mpu.getMotionInterruptStatus()) {
    /* Get new sensor events with the readings */
    sensors_event_t a, g, temp;
    mpu.getEvent(&a, &g, &temp);

    /* Print out the values */
    Serial.print("AccelX:");
    Serial.print(a.acceleration.x);
    Serial.print(",");
    Serial.print("AccelY:");
    Serial.print(a.acceleration.y);
    Serial.print(",");
    Serial.print("AccelZ:");
    Serial.print(a.acceleration.z);
    Serial.print(", ");
    Serial.print("GyroX:");
    Serial.print(g.gyro.x);
    Serial.print(",");
    Serial.print("GyroY:");
    Serial.print(g.gyro.y);
    Serial.print(",");
    Serial.print("GyroZ:");
    Serial.print(g.gyro.z);
    Serial.println("");

    // You can send any value at any time.
    // Please don't send more that 10 values per second.
    Blynk.virtualWrite(V0, a.acceleration.x);
    Blynk.virtualWrite(V1, a.acceleration.y);
    Blynk.virtualWrite(V2, a.acceleration.z);
    Blynk.virtualWrite(V3, g.gyro.x);
    Blynk.virtualWrite(V4, g.gyro.y);
    Blynk.virtualWrite(V5, g.gyro.z);
    delay(200);
  }
}

```

Fig. 7: Code snippet for sensor data capturing

platform you are using for project development. A step-by-step coding explanation is given in code snippet setting Wi-Fi and Blynk token shown in Fig. 5.

In this section, define the Blynk template ID, name, and authentication token according to your credentials for the Wi-Fi network and authentication token. Include the necessary libraries for Wi-Fi, Blynk, MPU6050 sensor, sensor events, and the Wire library for I2C communication. Fig. 6 shows the code snippet.

Create an instance of the Adafruit_MPU6050 class for the MPU6050 sensor and define variables for Blynk authentication, Wi-Fi SSID, and password. The BlynkTimer object is used for scheduling tasks. Fig.



Don't Be A Loser!

You don't know how much you don't know.

Read

electronics FOR YOU

to keep up-to-date with the tech world



To subscribe, visit efy.in or contact us at: 011-4059660
Email: support@efy.in

OR Scan This Code



Also available at all leading magazine outlets