



Output pins 4 through 7 of Arduino are connected to IN1 through IN4 pins of L293D, respectively. Ground

Mechanical arrangement of the bot or car is

The Arduino Uno can be programmed with the Arduino software (IDE). Switch off the Bluetooth module or disconnect it from Arduino while burning the `asc_car.ino` sketch into the Arduino Uno.


Connect smartphone with HC-05 module. After all the connections and mechanical arrangements are complete, download Arduino Bluetooth Controller app from Google Play Store in Android smartphone. There are many similar apps available on Play Store. This project uses ArduinoRC—an Arduino Bluetooth Controller app developed by Estacado's Ltd. Open the ArduinoRC application in Android smartphone and connect with the HC-05 device by typing '1234' or '0000' as pin for pairing with HC-05.

Feeding values in the app.

Press 'Proceed' option to connect your smartphone with the HC-05 module. You will see a screen on your Android phone as shown in Fig. 4. Select 'Vehicle' mode, open the menu in the top-right corner and select 'Set Commands' option. Set value '4' for 'Stop' button in the application. Similarly, feed values 0, 1, 2 and 3 for Gesture_Front, Gesture_Left, Gesture_Right and Gesture_Back, respectively.

Connect 12V battery supply to L293D module. Now the bot is ready to be controlled with your smartphone. You can control your bot by tilting the smartphone in different positions. Tilt your phone forward or backward to move the bot in forward or backward direction. Similarly, tilt your phone to the right or left to make the bot take right or left turn, respectively.

With a slight tweak in the circuit, you can also use this app to control lights, horns and music systems by tilting the smartphone in different directions. **EEY**



Follow us on Twitter @OpenSourceForU