

TABLE I
PIN CONNECTIONS OF
LCDs TO ARDUINO BOARD

Arduino pin	LCD pin
Digital 4	D7 (LCD1-LCD3)
Digital 5	D6 (LCD1-LCD3)
Digital 6	D5 (LCD1-LCD3)
Digital 7	D4 (LCD1-LCD3)
Digital 8	EN3 (LCD3)
Digital 9	RS3 (LCD3)
Digital 10	EN2 (LCD2)
Digital 11	RS2 (LCD2)
Digital 12	EN1 (LCD1)
Digital 13	RS1 (LCD1)

All the three LCDs are configured in 4-bit mode. Common data lines of all the LCDs (D4 through D7) are connected to digital pins 4 through 7 of Arduino Uno. RS and EN control pins of LCDs are connected to different digital pins of Board 1. Pin-to-pin connections between

TABLE II
JUMPER SETTINGS FOR DIFFERENT DATA DISPLAY

Jumper setting	LCD display
Connect SJ1 and SJ2 across CON1	LCD1 data display
Connect SJ3 and SJ4 across CON2	LCD2 data display
Connect SJ5 and SJ6 across CON3	LCD3 data display
Connect SJ1 through SJ4 across CON1 and CON2	LCD1 and LCD2 data display
Connect SJ3 through SJ6 across CON2 and CON3	LCD2 and LCD3 data display
Connect SJ1, SJ2 across CON1 and SJ5 and SJ6 across CON3	LCD1 and LCD3 data display
Connect SJ1 through SJ6 across CON1, CON2 and CON3	LCD1, LCD2 and LCD3 data display
Disconnect all SJ1 through SJ6	LCD1, LCD2 and LCD3 data display off

LCDs and the Arduino Uno board are shown in Table I.

First LCD. If you want to display data on the first LCD (LCD1) only, connect RS and EN pins of LCD1 to Arduino using SJ1 and SJ2 across connector CON1. Remove SJ3 through SJ6 so that RS and EN pins of the other two LCDs are not used. Thus it is possible to send data to the selected LCD while using com-

mon data lines of the LCDs.


Second LCD. To display data on the second LCD (LCD2) only, connect RS and EN pins of LCD2 using SJ3 and SJ4. Remove SJ1, SJ2, SJ5 and SJ6 to ensure that RS and EN pins of the other two LCDs are not used.

Third LCD. Similarly, to display data on the third LCD (LCD3) only, connect RS and EN pins of



THE BEST CONNECTOR SYSTEMS FOR HOME APPLIANCES, AUTOMOTIVES AND HVAC

www.stocko-contact.com



STOCKO CONTACT GmbH. World's leading manufacturer of Crimp and Insulation Displacement Connector (IDC) systems. STOCKO CONTACT GmbH boasts of an in-house Machine Department with Hand Operated Tools, Semi Automatic as well as Fully Automatic Machines. STOCKO parts are widely used in Automobile, HVAC and Home Appliances Industry. In India and Sri Lanka, already 11 major projects running with Stocko parts.

Do visit us to explore the world of German made Crimp, IDC and Terminating Machines to provide you the best solution for your wire harness.

Applications

- Stoves
- Air Conditioners
- Washing Machine
- Lighting Systems
- Refrigerators
- HVAC Industry

- IDC Tools and Machines
- Insulation Displacement connectors
- Multiple connector systems in various pitches
- Crimp contacts in several material with different plating



Florina Apts., 6th Floor, S.No. 2/1/7 Erandwane, Off. Karve Road, Pune 411 004, India. Tel.: 020-25465915, Nachiket: +91-8600182797

AUTHORIZED DISTRIBUTORS IN INDIA, SRI LANKA AND UAE

www.aurocontrols.com