

Fig. 3: Actual-size PCB layout for stereo amplifier




Fig. 4: Components layout of the PCB

a 4-ohm, 6W speaker each to LS1 and LS2, respectively, as shown in Fig. 2.

Now slowly increase the volume control (VR1) after connecting the signal generator (with 1kHz signal) to the left input. You'll hear sound coming from LS1 speaker. Similarly, connect the signal generator to the right input and slowly increase the volume control (VR2) to hear sound from LS2 speaker.

If you do not have a signal generator, use a metal screwdriver for testing your prototype. Gently touch the screwdriver on the right and left inputs of your prototype. You will hear a humming sound from the right and left speakers.

Finally, connect a stereo jack to the input (CON2) of your amplifier. Then feed an audio signal to CON2 from an audio source such as an MP3

PARTS LIST

Semiconductors:

IC1 - TDA1517 audio amplifier

Resistors (all 1/4-watt, $\pm 5\%$ carbon):

VR1, VR2 - 10-kilo-ohm potentiometer

Capacitors:

C1, C2 - 220nF ceramic disk

C3 - 100 μ F, 35V electrolytic

C4-C6 - 1000 μ F, 35V electrolytic

Miscellaneous:

CON1 - 2-pin terminal connector

CON2 - 3-pin male Berg strip connector

LS1, LS2 - 4-ohm, 6W loudspeaker

- Heat-sink for TDA1517

- Stereo jack

- 2-pin terminal connector for LS1 and LS2

- 12V/14.4V DC source

player or a computer. Adjust VR1 and VR2 to middle positions. You'll hear clean audio output from the speakers (LS1 and LS2). **DSV**



Raj K. Gorkhali is an electronics hobbyist and a regular contributor to EBY

www.opensourceforu.com

Job Guaranteed.

You don't need a training institute. Just do it yourself.

WORK WITH OPEN SOURCE.

TO READ OUR PRINT EDITION Visit: <http://subscribe.eyfindia.com>

TO READ OUR EZONE EDITION Visit: <http://ezine.eyfindia.com>

WORLD'S LEADING PUBLICATION ON OPEN SOURCE

Looking for marketing solutions to engage with cutting edge techies?
Contact us at growmybiz@eyfindia.com OR call us at +91-9811155335.

Demand for Open Source is sky rocketing. Be it for managing IT infrastructure or development of software —Open Source experts are what organisations are seeking. Develop expertise in an Open Source stack, and watch your career graph zoom.

You don't need a training institute for this. You can do it yourself. And, Open Source For You can be your friend and a guide through this journey.

