

*Fig. 3: Setting the SPI pin and display driver name*

Fig. 4: Code for getting RSSI of the networks

Fig. 5: Code to display RSSI of the Wi-Fi networks

Circuit diagram of the Wi-Fi analysing smart watch is shown in Fig. 2. It is built around LCD (MOD1), USB micro cable (MOD2), ESP12F (MOD3), and MCP73812T (MOD4). Connect the components as per circuit diagram, which has two parts—first, voltage regulation plus 3.3V cell charging part and, second, the actual smart watch circuit that is connected to the battery through jumper pin JP1.

Next, create the setup function and then the loop function where we scan the Wi-Fi network and extract the RSSI of all Wi-Fi networks, which gives us the network strength of all nearby Wi-Fi networks. The ana-