SimpleGrid problems compiled to d-DNNF with d4 (projected, no evidence)

Instance	Horizon	Circuit file	d4 time (s)	Total time (s)	CNF variables	CNF clauses	Projected variables	Circuit nodes	Circuit edges	Model count (verified)	Query with 2 obs. (s)
grid3x3-1	5	grid3x3-1.dnnf	0.03	1.9	141	818	98	43	81	18	0.001
grid3x3-2	5	grid3x3-2.dnnf	0.03	1.9	141	818	98	45	85	18	0.001
grid3x3-3	5	grid3x3-3.dnnf	0.04	1.9	141	818	98	45	85	18	0.001
grid3x3-4	5	grid3x3-4.dnnf	0.04	1.9	141	818	98	45	85	18	0.001
grid4x4-1	7	grid4x4-1.dnnf	0.04	1.9	400	2,609	291	228	451	140	0.006
grid4x4-2	7	grid4x4-2.dnnf	0.04	1.9	400	2,609	291	228	451	140	0.006
grid4x4-3	7	grid4x4-3.dnnf	0.04	1.9	400	2,609	291	228	451	140	0.007
grid4x4-4	7	grid4x4-4.dnnf	0.04	1.9	400	2,609	291	228	451	140	0.006
grid5x5-1	9	grid5x5-1.dnnf	0.14	2.3	865	5,994	644	2,606	5,208	2,100	0.165
grid5x5-2	8	grid5x5-2.dnnf	0.06	1.9	760	5,248	564	393	781	315	0.023
grid5x5-3	9	grid5x5-3.dnnf	0.10	2.1	865	5,994	644	1,032	2,059	1,372	0.088
grid5x5-4	8	grid5x5-4.dnnf	0.05	1.7	760	5,248	564	399	793	280	0.026
grid6x6-1	11	grid6x6-1.dnnf	1.54	7.5	1,596	11,477	1,205	24,754	49,539	36,510	0.924
grid6x6-2	11	grid6x6-2.dnnf	2.02	9.6	1,596	11,477	1,205	29,556	59,122	28,302	1.78
grid6x6-3	10	grid6x6-3.dnnf	0.28	2.9	1,440	10,333	1,085	3,860	7,717	3,570	0.425
grid6x6-4	11	grid6x6-4.dnnf	1.63	8.5	1,596	11,477	1,205	26,389	52,808	28,302	2.12
grid7x7-1	12	grid7x7-1.dnnf	6.27	29.5	2,436	17,936	1,854	73,184	146,525	96,558	6.22
grid7x7-2	12	grid7x7-2.dnnf	4.54	20.9	2,436	17,936	1,854	57,227	114,500	65,472	4.88
grid7x7-3	12	grid7x7-3.dnnf	6.60	27.9	2,436	17,936	1,854	91,315	182,661	86,856	4.18
grid7x7-4	12	grid7x7-4.dnnf	8.67	40.2	2,436	17,936	1,854	109,265	218,648	103,620	7.44

Each problem's evidence-free recognition theory — the problem at its recognition horizon, with the goal literals as the hypotheses, as recognize.sh builds it — compiled by marginals.sh `--solver` d4 `--project`. The projection keeps the drive actions and the final-slice goal atoms, and FiFO first verifies that they determine every other atom, so the projected circuit gives exact counts; any pinned observations are unit literals over the kept actions, so one saved circuit answers every evidence file by conditioning, without recompiling. CNF variables and clauses are those of the ground theory d4 is given; projected variables are the ones it keeps. d4 time is the d4 run alone; total time is the whole marginals.sh run (reading the theory, the projection check, d4, importing and saving the circuit, and the marginals of the unconditioned circuit). Circuit nodes and edges are those of d4's decision-DNNF, before FiFO smooths it. Times are wall-clock, 2 compilations at a time, each limited to 30 minutes. SBCL ran with an 8 GB heap and a 1 GB control stack, d4 with a 64 MB stack (the defaults, 1 GB, 2 MB and 8 MB, are too small for the larger circuits). The circuits were imported by FiFO with its d4 importer rewritten to use bit-vector scopes and iterative traversal (branch ddnnf-import-bitvector-scopes); the released importer runs out of memory on circuits of about a million nodes. Model count (verified) is the number of models of the compiled circuit (all literals set to 1 in the smoothed circuit), that is, the number of truck walks the theory allows. Every circuit kept was checked against an independent count of those walks by dynamic programming over the grid (H-1 steps, each a drive to a neighbouring cell or a wait, from p1-1 to a goal cell), which also agrees with sharpSAT on every problem shown; the two counts were equal for every circuit in the table. Grids larger than 7×7 are omitted: from 8×8 on, d4 often crashes (bus error or segmentation fault) or returns a wrong circuit without any error, and repeated runs on the same CNF give different circuits. Query with 2 obs. is the time to recompute every marginal of the saved circuit conditioned on two observations — the first two drives of a shortest plan to the problem's alphabetically first destination, pinned to steps 1 and 2 (evidence/PROBLEM-DESTINATION-obs2.txt) — as marginals.sh `--circuit --evidence-file` does: the observations are unit literals over kept atoms, so the circuit is clamped and re-evaluated, not recompiled. It is timed inside SBCL, the median of 5 repetitions, and excludes starting SBCL and loading FiFO (about 1.2 s) and reading the circuit file (0.001–0.48 s). Each answer was checked: both observed drives have probability 1, and the final-slice goal marginals sum to 1. Most of the query time is FiFO's backward pass, which for an AND node with k children recomputes the k-1 sibling products for each child (k^2 multiplications; the largest smoothed AND node of 7×7-4 has 1,007 children), not the circuit size itself.