hwde-led-test: board report

The first board the Hive designed with the hwde module

2026-10-28

Contents

1 What this is 1

2 What the board is 2

3 Schematic 2

4 Layout 3

5 BOM and cost 5

6 Every gate result 6

7 Decisions made along the way 7

8 Decisions waiting for you 7

9 The run: time per stage 8

10 Snags the run hit 8

11 How this report was made 9

1 What this is

This report covers **hwde-led-test**, a tiny 2-layer board that lights one green LED from 5 V. It was the first board the Hive designed end to end with the hive-hwde module, on 2026-10-28. It went from a written brief to checked fab files in about 45 minutes, to prove the pipeline runs inside the Hive. **It has not been ordered or quoted.** Ordering is your call.

The run went on through the stages while three sign-offs were still waiting for your answer: H1 (architecture), H2 (schematic) and H4 (verified board). H4 also asks you to waive two verify warnings. Those five decisions are in section 8, each with what it asks and a recommended answer. This report puts everything you need for them in one place.

Board	2 layers, 1.6 mm FR-4, 1 oz, HASL (JLC2313), 13.4 x 10.5 mm, no holes
Circuit	J1 5 V header, C1 4.7 µF input cap, R1 470 Ω, D1 green 0603 LED (about 4 mA)
Gates	ERC, place, routed DRC, verify (14 checks), JLC DFM: **all pass**
Open	2 verify warnings not waived; H1, H2 and H4 not answered
Parts cost	about $0.05 a board at LCSC single-piece prices (JLC fees not quoted)
Run time	about 45 minutes, brief to DFM-clean package; 9 subagents, 325k tokens




Figure 1: The board, 3D render (iso)

2 What the board is

The brief asked for "a tiny 2-layer board that lights one LED from 5 V":

- **Input:** 5 V DC (4.75–5.25 V) on J1, a 2-pin 2.54 mm header. Pin 1 is +5V (square pad, marked +) and pin 2 is GND (marked —). It is fed from a bench supply or a USB 5 V lead. As the brief asked, there is no reverse-polarity protection.
- **C1:** 4.7 µF 16 V X5R 0603 across the input, next to J1.
- **R1 + D1:** 470 Ω feeds a green 0603 LED (KT-0603G). At the LED's listed forward voltage of 3.1 V, that gives 3.5 mA at 4.75 V, 4.0 mA at 5.0 V and 4.6 mA at 5.25 V, inside the brief's 3–5 mA.
- **Layout:** all SMD parts are on top. J1 is through-hole on the left edge, and the bottom layer is a GND pour.
- **Built:** 5 boards if it is ever built. It is meant for room temperature on a bench, with no enclosure.

3 Schematic

There is one sheet with four parts and three nets: +5V, GND and LED_A. ERC reports 0 errors and 0 warnings, and a fresh-context reviewer found 0 errors (`reports/review-schematic.md`). The full sheet is `reports/schematic.pdf`. Below is the drawn area, cropped from that sheet.




Figure 2: Schematic (cropped from reports/schematic.pdf)

The circuit is right, but the sheet reads poorly. The generator puts each net label on top of its pin number, so "+5V" runs into "1". The circuit sits small in one corner of an A4 sheet, and the "K"/"A" text overlaps inside D1's symbol. This doesn't change the netlist, but it makes the sheet harder to check by eye (snag 14).

4 Layout

The board is 13.4 x 10.5 mm, with 2.0 mm corner radii. All four parts sit on the top side in one row: J1 on the left edge, C1 beside it, then R1 and D1. +5V runs from J1 pin 1 through C1's pad to R1. LED_A runs from R1 to D1's anode. C1's GND and D1's cathode each drop through their own via to the bottom GND pour, and J1 pin 2 is thermal-tied to that pour.

The two copper layer views below were made by the module's `layer_views` from the final routed board. Net names are drawn on the copper, and both layers are seen from the top. The vector PDFs, which stay sharp when zoomed, are `img/hwde-led-test_F_Cu.pdf` and `img/hwde-led-test_B_Cu.pdf`.




Figure 3: Top copper (F.Cu), with top silk, fab and courtyard




Figure 4: Bottom copper (B.Cu): the GND pour, seen from the top

The 3D renders come from KiCad 10.0.6, with the parts' EasyEDA 3D models pulled fresh for this report:




Figure 5: Top




Figure 6: Bottom: J1's two through-hole pads, the GND pour and the two GND vias

5 BOM and cost

Ref	Part	Value	Package	LCSC	JLC class	Price (1 pc)
J1	XFCN PZ254V-11-02P	1x2 header	2.54 mm THT	C492401	Extended	$0.0187
C1	Samsung CL10A475KO8NNNC	4.7 µF 16 V X5R	0603	C19666	Basic	$0.0169
R1	UNI-ROYAL 0603WAF4700T5E	470 Ω 1 % 100 mW	0603	C23179	Basic	$0.0023
D1	Hubei KENTO KT-0603G	green, Vf 3.1 V at 5 mA	0603	C12624	Extended	$0.0117
					per board	**$0.0496**

- **Parts:** about $0.05 a board, or $0.25 for the 5 boards in the brief, at LCSC's single-piece prices from `parts/parts.json`. All four parts were in stock when sourced, with 417k to 4.8M units.
- **Fees:** the PCB, assembly and JLC's Extended-part fees were **not quoted**. A quote is part of P10, which is yours. DigiKey and Mouser prices weren't looked up because they need API keys the Hive doesn't hold.
- **Extended parts:** D1 and J1 are both Extended, so JLC charges its Extended-part fee for each one. They may also need buying into your JLC parts inventory first (`fab/prebuy.csv`). There is no Basic green LED in 0603, only in 0805.
- **J1 in the CPL:** `fab/CPL.csv` lists J1 as a top-side SMT placement (`smt_placed`), even though it is through-hole. At order time, either hand-solder J1 or order it as THT assembly (snag 13).

The fab package is in `fab/`: `hwde-led-test_gerbers.zip` (the JLC layer set plus drill, 11 files), `BOM.csv`, `CPL.csv` and `prebuy.csv`.

6 Every gate result

Each gate was run through the module's `gate` with `--workspace`, so each one is recorded in `state.json`. The table shows the last result for each gate.

Gate	Stage	Result	Attempts	Failed	Why a run failed
ERC (`erc`)	P4	**pass**: 0 errors, 0 warnings	4	0	(re-runs after a decoupling.json change)
Placement (`place`)	P6	**pass**	6	1	A centred outline grow left J1 3.0 mm from its edge (limit 2.5); restored and redone
Routed DRC (`drc_routed`)	P7	**pass**: 0 errors, 0 warnings, 0 unconnected	3	0	
Verify suite (`verify`)	P8	**pass**: 14 of 14 checks ran, 0 errors, **2 warnings**	5	1	check_pdn: +5V had no cap tied to it until C1 was recorded against J1.1 (since snag 5's fix, check_pdn finds C1 on the board)
JLC DFM (`dfm`)	P9	**pass**: 0 findings	1	0	

The verify suite's checks are return path, current, decoupling, diff pairs, creepage, thermal, silk, route style, mating, PDN, ratings, BOM sync, mate pins and 3D model paths. All of them pass except two, which give the warnings covered in section 8. The DFM gate ran copper, copper-to-edge, drill, hole-to-edge, silk, polarity, placement, BOM, release and castellation. Its `placement_visual` step didn't run, and the gate isn't strict, so that didn't fail it.

For this report, KiCad's own DRC (with schematic parity) and ERC were run again on the committed board, and both report 0 violations. Two fresh-context reviewers also read the design:

- **Schematic** (`reports/review-schematic.md`): 0 errors and 2 warnings.
  - The LED current is short of margin if D1's real Vf is high.
  - The LCSC field name for the BOM was wrong. It was fixed at P9.
- **Board** (`reports/review-board.md`): 0 errors and 3 warnings, all fixed.

- The board was below JLC's 10 mm assembly minimum, so it was grown from 13.05 x 9.08 to 13.4 x 10.5 mm.
- J1 had no polarity mark, so +/− were added.
- The C1 label was ambiguous, so it was moved.

7 Decisions made along the way

Each of these decisions is recorded in `state.json` (`decisions`) with its reason:

1. **There was no research stage (P1).** A header, a cap, a resistor and an LED need none.
2. **The design went ahead with a coverage gap.** hwde has no checklist for an LED indicator, and its rule is to research such a gap. The run skipped that research for a textbook LED branch and put the choice to you at H1.
3. **R1 is 470 Ω, not the 680 Ω in the H1 packet.** At D1's listed Vf of 3.1 V, 680 Ω gives only 2.4–2.8 mA. The 3.1 V comes from LCSC's listing because the datasheet wouldn't download. If the real Vf is as high as 3.4 V, the current falls to about 2.8 mA at 4.75 V, and the LED is still lit.
4. **D1 is a JLC Extended part.** There is no Basic 0603 green LED.
5. **The 0603 courtyards were widened by hand to ±1.40 x ±0.70 mm.** The EasyEDA footprints used the body outline as the courtyard, which didn't cover the pads.
6. **D1's cathode is pad 1.** This comes from the symbol and the silk chamfer, not the datasheet, which wouldn't download.
7. **The outline was fitted with a 2.0 mm margin.** Margins of 1.0 and 1.5 mm clipped the reference text. The board was then grown to 10.5 mm tall for JLC assembly.
8. **The run stopped at P9.** There was no quote, no order and no board guide.

8 Decisions waiting for you

This report stands in for the three sign-off packets and the two waivers. The run went on while they were open; any "no" sends that stage back for rework.

H1: architecture. *Approve the architecture as is?* The architecture is four parts on one sheet, 2 layers, JLC2313 1.6 mm HASL, with size set by placement and no holes. The research for the LED-indicator coverage gap was skipped (decision 2). The packet proposed R1 = 680 Ω, which became 470 Ω at P3 (decision 3). **Recommended: yes.** If you want a different LED colour or current, say so; R1 and D1 are the only parts that change. *To read:* `requirements.md`, `architecture/blocks.md`, `log/P2-digest.md`.

H2: schematic. *Approve the schematic?* ERC is 0/0, the netlist audit is clean, and the reviewer found 0 errors. The parts are J1 C492401, C1 C19666, R1 C23179 and D1 C12624. D1 and J1 are Extended. The reviewer's two warnings are the Vf margin (decision 3) and the BOM field name, which was fixed. **Recommended: yes.** If you want the sheet to read better first, redraw it (snag 14); the netlist and board wouldn't change. *To read:* `reports/schematic.pdf`, `reports/review-schematic.md`, `reports/erc-waivers.md`.

H4: verified board. *Approve the board as verified?* All five gates pass on the final board (section 6), and the reviewer's 3 warnings are all fixed. The fab package is complete. **Recommended: yes.** It's a test board and nothing is ordered. If you ever do order it, re-check snag 13 (J1 as THT) and D1's datasheet first. *To read:* the renders above, `reports/review-board.md`, `fab/`, `log/P8-digest.md`, `log/P9-digest.md`.

Waiver 1: `check_route_style`, a jog on /LED__A. *Waive it?* There is a 0.15 mm sidestep on F.Cu at (17.06, 18.98), because R1 pad 2 (y 18.90) and D1's anode (y 19.05) don't line up. It is cosmetic and changes nothing electrically. The fix is to move D1 up 0.15 mm and re-route that one net. **Recommended: waive.** Fix it if the board is touched again.

Waiver 2: `check_ratings`, D1 has no voltage rating. *Waive it?* The ratings check found no voltage-rating attribute on D1. (It also named R1 until snag 4 was fixed: it now reads R1's "Voltage-Supply(Max)", 75 V.) D1's reverse rating is unknown without its datasheet. D1 only sees reverse voltage, up to 5.25 V, if the leads are swapped. Green InGaN LEDs are usually rated for 5 V reverse, and the +/− silk at J1 makes a swap less likely. **Recommended: waive** for a bench test board.

The hive-hwde lead also asked whether to treat the board as a passed smoke test and move on. If all five answers are yes, it is one.

9 The run: time per stage

These times come from the `phase` events in `state.json`, on 2026-10-28, local time (EDT):

Stage	Start	Minutes	Who did it
P0 intake	09:25	1.5	requirements-analyst (sonnet)
P1 research	09:26	0	none (decision 1)
P2 architecture	09:26	2.5	architect (sonnet)
P3 parts + library	09:29	3.5	part-sourcer, librarian (sonnet)
P4 schematic	09:33	11.5	schematic-block, schematic-reviewer (opus)
P5 board setup	09:44	0.5	inline
P6 placement	09:45	10	placement (opus) and outline fit
P7 routing	09:55	4.5	router (opus), freerouting
P8 verification	09:59	7	verify-reviewer (opus) and 3 fixes
P9 DFM + fab	10:06	4	inline
Total		**about 45**	9 subagent spawns, 324,782 tokens

That time includes the module fixes made along the way (symdir flattening, the 3D render shim, the Xvfb GLX switch). No fix-loop budget was spent: the two gate failures (place and verify) were each fixed directly. This run is the baseline that later boards, starting with hifi-receiver-2, are measured against.

10 Snags the run hit

These are places where hwde's own tools got in the way. Following the module's rule, each one becomes a hive-hwde change rather than a workaround on the board. Snags 1–12 come from the run itself and are already filed as seven briefs. Snags 13–17 turned up while making this report; 13–16 are filed as their own briefs.

#	Where	What	Filed as
1	`scripts/lib/env.py`, `schlib.py`	kicad-sch-api can't read KiCad 10's `.kicad_symdir` libraries; `bin/hwde` flattens them instead	261028-141924-4dae199a93
2	`scripts/kc.py render_env`	The 3D loaders are only looked for at distro paths and are missed in the AppImage; shimmed in `bin/hwde`	261028-141924-4dae199a93
3	`agents/part-sourcer.md`	No `refdes` or `attributes` per parts line, so the BOM had no LCSC column and ratings went unread	261028-141930-114d313009 (fixed: the sourcer copies the row whole, and bom_cpl reads the board's `LCSC Part` field)
4	`check_ratings.py V_ATTR_RE`	LCSC's "Voltage-Supply(Max)" isn't read, so R1's 75 V shows as unrated (waiver 2)	261028-141930-114d313009 (fixed)

#	Where	What	Filed as
5	`check_pdn.py` / decoupling	A board with no IC gets no cap association for its bulk cap	261028-141930-114d313009 (fixed: check_pdn counts a cap straight across the rail and ground)
6	`lib_pull.py` (EasyEDA)	0603 courtyards are the body outline, and nothing caught it	261028-141932-4f01e64893
7	`board_edit.py --outline fit`	The fit margin ignores reference text, and a centred resize can push an edge connector out of tolerance	261028-141932-4f01e64893
8	`knowledge/checklists/`	There is no LED-indicator checklist, so every LED reads as a coverage gap	261028-141932-9b95b3083b
9	datasheets from wmsc.lcsc.com	They arrive as a ~140-byte stub through the proxy, so there were no extractions or `fp_verify` and D1's polarity is unconfirmed	261028-141933-6a25b2c09c
10	`kicad/gen/root.py` regeneration	New instance UUIDs break board parity	261028-141934-60618887e0
11	KiCadRoutingTools	It wasn't in `/hive/tools`; it is now, and the skill still has to find it	261028-141924-4dae199a93
12	`report_gen.py`, board guide	They need the pdf-material-builder house style, which isn't here, so this report was built with pandoc and lualatex instead	261028-141935-42bdc24230
13	`bom_cpl.py` assembly class	J1 (THT) is classed `smt_placed` and placed in the CPL	261028-144247-0a37b2952e
14	`kicad/gen` schematic generator	Net labels sit on pin numbers, and the circuit is tiny in one corner of an A4 sheet	261028-144249-63ddfa029b
15	`lib_pull.py`	Parts that already exist get no 3D models, so the README's "re-pull with lib_pull" fetches none, and `--overwrite` would undo the hand-widened courtyards	261028-144250-cf7085cecf
16	`report_gen.py` file names	It looks for `verify_all.json`, `fab_export.json` and `bom_cpl.json`, but the run saved `verify-summary.json`, `fab-export.json` and `bom-cpl.json`	261028-144253-daf2ceb304
17	`bin/hwde`	It was committed without its execute bit, so `bin/hwde ...` fails from a fresh clone	fixed with this report

11 How this report was made

- **Renders and layer views:** the module's `layer_views`, on the committed `kicad/hwde-led-test.kicad_pcb`. The 3D models were pulled into a scratch directory with `lib_pull --out-dir` and only `aiee.3dshapes` was copied into `lib/` (snag 15). It stays gitignored.
- **Layer PNGs and the schematic crop:** `pdftoppm`, from the layer PDFs and `reports/schematic.pdf`.
- **Data:** everything else comes from the board's own records: `state.json`, `parts/parts.json`, `reports/`, `log/`, `fab/`, and the sign-off packets the run sent to the hwde lead.
- **This document:** `report/hwde-led-test-report.md` is the source. pandoc 3.9 turned it into `hwde-led-test-report.tex`, and lualatex built `hwde-led-test-report.pdf` from that. The skill's own `report_gen` couldn't be used because it needs the house style (snag 12).
- **To rebuild:** `report/build.sh`, with pandoc on PATH.