

```

#include "neopixel.h"

int ButtonPIN = D2;    // sets the input button to read from pin digital 2
bool ButtonNow = FALSE; // sets the initial status of the button to be
                        // not pressed

int PIXEL_PIN = D4;    // pin the pixel data is sent to
int PIXEL_COUNT = 2;    // number of LEDs
int PIXEL_TYPE = WS2811; // types of LEDs

Adafruit_NeoPixel strip = Adafruit_NeoPixel(PIXEL_COUNT, PIXEL_PIN,
PIXEL_TYPE);

// setup() runs once, when the device is first turned on.
void setup() {
    pinMode(ButtonPIN, INPUT_PULLDOWN);
    strip.begin();
    Serial.begin(9600);
    // Put initialization like pinMode and begin functions here.
}

// loop() runs over and over again, as quickly as it can execute.
void loop() {

    ButtonNow=digitalRead(ButtonPIN);    // sets the button now variable to
    read from the pin the button sends data to

    if (ButtonNow == HIGH) {    // if the button is pressed the lights are
    turned on

        int PixelColorBlue = strip.Color( 0 , 0, 255);    // variable
        PixelColorBlue is set to output a blue color
        int PixelColorYellow = strip.Color( 244, 232, 104); // variable
        PixelColorYellow is set to output a yellow color

        strip.setPixelColor(0, PixelColorBlue); // sets the first LED to be
        blue
    }
}

```

```
        strip.setPixelColor(1, PixelColorYellow);    // sets the second LED to
be yellow
        strip.show();    // changes the lights
    }

    else {    // if the button is not pressed turns the lights off

    int PixelColorOff = strip.Color(0,0,0);    // sets the variable
PixelColorOff to output no light

    strip.setPixelColor(0, PixelColorOff);    // sets the lights to be off
        strip.setPixelColor(1, PixelColorOff);
        strip.show();    // changes the lights
    }

    // The core of your code will likely live here.

}
```

[Link to Micro Project Demo](#)

My micro project consists of a set of 2 LEDs that turn on blue and yellow when both of the buttons are pressed, but not when one of or neither of the buttons are pressed. I did this by wiring the two buttons in series and reading the status of the buttons using one of the digital pins. If the digital pin reads a voltage from the buttons then it sends a signal through another digital pin to the lights and turns them on. Once the program detects that the buttons are no longer pressed then the lights are turned off.